

M-7000 Series Address Mapping Table

V1.18, September 2025



授權者: Wayne Chen
編輯者: Janice Hong

Revision History

Date	Revision	Changes
2025/9/12	1.18	Modify default type code of M-7018Z, default type code and slew rate of M-7028
2025/6/9	1.17	Modify description of enabling channel
2025/6/3	1.16	Modify description of enabling channel and alarm limit
2025/5/29	1.15	Add data format and factory default
2022/4/18	1.14	Add register 40865 ~ 40880 to M-7005
2019/1/28	1.13	Add register 00276 to M-7018Z
2018/10/31	1.12	Add M-7028

Revision History 2

M-7000 Address Mapping (Base 1)..... 4

M-7002..... 4

M-7004..... 7

M-7005..... 12

M-7011..... 15

M-7013P..... 18

M-7015/M-7015P 21

M-7016..... 24

M-7017/M-7017R..... 27

M-7017C/M-7017RC..... 29

M-7017R-A5..... 31

M-7017RMS 33

M-7017Z..... 35

M-7018/M-7018R..... 37

M-7018Z..... 39

M-7018-16 41

M-7019R 43

M-7019Z..... 46

M-7022..... 49

M-7024..... 52

M-7024R 55

M-7024U 58

M-7026..... 62

M-7028..... 66

M-7033..... 69

M-7000 DIO..... 70

M-7080..... 72

M-7080B 74

M-7084..... 76

M-7088..... 78

M-7000 Address Mapping (Base 1)

M-7002

Address	Description	Data Format	Attribute	Factory Default
00001 ~ 00004	Digital output	0: Off 1: On	R/W	-
00065 ~ 00069	Digital input latch high	0: Normal 1: Latched	R/W	-
00073 ~ 00076	Digital output latch high	0: Normal 1: Latched	R/W	-
00097~ 00101	Digital input latch low	0: Normal 1: Latched	R/W	-
00105 ~ 00108	Digital output latch low	0: Normal 1: Latched	R/W	-
00129 ~ 00132	Digital output safe value	0: Off 1: On	R/W	0
00193 ~ 00196	Digital output power-on value	0: Off 1: On	R/W	0
00257	Communication protocol	0: DCON 1: Modbus RTU	R/W	1
00259	Filter settings	0: 60 Hz rejection 1: 50 Hz rejection	R/W	0
00260	Host Watchdog mode 0: The same as I-7000 series module (old mode) 1: AO and DO commands can be used to clear the Host Watchdog timeout status (new mode)	0: Old mode 1: New mode	R/W	0
00261	Enables or disables the Host Watchdog	0: Disabled 1: Enabled	R/W	0
00262	Enables or disables the alarm function	0: Disabled 1: Enabled	R/W	0
00263	Alarm mode	0: Momentary 1: Latch	R/W	0
00264	Clear DI/O latch	1: Clear	W	-
00265	Clear all DI counters	1: Clear	W	-
00269	Modbus data format	0: Hexadecimal 1: Engineering	R/W	1
00270	Host Watchdog timeout status. Write 1 to clear the Host Watchdog timeout status	0: Normal 1: Host watchdog timeout	R/W	-
00271	AI filter format	0: Normal 1: Fast	R/W	0
00272	Write 1 to reload the factory calibration parameters	1: Reload	W	-

00273	Reset status 0: not the first the status has been read after being powered on 1: the first time the status has been read after being powered on	0: Not reset 1: Reset	R	-
00289 ~ 00292	Low alarm status of channels 0 to 3, write 1 to clear	0: Normal 1: Alarmed	R/W	-
00305 ~ 00308	High alarm status of channels 0 to 3, write 1 to clear	0: Normal 1: Alarmed	R/W	-
00513 ~ 00517	Clear digital input counter channel 0 to 4	1: Clear	W	-
10033 ~ 10037	Digital input status for channels 0 to 4	0: Off 1: On	R	-
30001 ~ 30004	Analog input value for channels 0 to 3	-32768 to 32767 (0x8000 to 0x7FFF)	R	-
30097 ~ 30101	Digital input counter for channels 0 to 4	0 to 65535	R	-
40225 ~ 40228	High alarm value for analog input channels 0 to 3	-32768 to 32767 (0x8000 to 0x7FFF)	R/W	32767 (0x7FFF)
40233 ~ 40236	Low alarm value for analog input channels 0 to 3	-32768 to 32767 (0x8000 to 0x7FFF)	R/W	-32768 (0x8000)
40257 ~ 40260	Type code for analog input channels 0 to 3	0x07: 4 ~ 20 mA 0x08: ±10 V 0x09: ±5 V 0x0A: ±1 V 0x0B: ±500 mV 0x0C: ±150 mV 0x0D: ±20 mA 0x1A: 0 ~ 20 mA	R/W	0x08
40481	Firmware version (low word)	0x000z for xy.z	R	-
40482	Firmware version (high word)	0x0x0y for xy.z	R	-
40483	The name of the module (low word)	0x0200	R	0x0200
40484	The name of the module (high word)	0x0070	R	0x0070
40485	Module address, valid range: 0x1 ~ 0xF7	1 to 247	R/W	1
40486	Bits 5:0: baud rate Bits 7:6: parity	Bits 5:0, baud rate 03: 1200 04: 2400 05: 4800 06: 9600 07: 19200 08: 38400 09: 57600 0A: 115200 Bits 7:6, parity	R/W	6

		00: N81 01: N82 02: E81 03: O81		
40488	Response delay time, 0~30, in ms	0 to 30	R/W	0
40489	Host Watchdog timeout value, 0 ~ 255, in 0.1s	0 to 255	R/W	255
40490	Enable/disable analog input channel, bit 0 for channel 0, bit 1 for channel 1, etc. 0 to disable and 1 to enable.	0 to 15	R/W	15
40492	Host Watchdog timeout count, write 0 to clear	0 to 65535	R/W	-

M-7004

Address	Description	Data Format	Attribute	Factory Default
30001 ~ 30020 40001 ~ 40020	Temperature readings of port 0 in 0.01°C	-32-768 to 32767	R	-
30021 ~ 30040 40021 ~ 40040	Temperature readings of port 1 in 0.01°C	-32768 to 32767	R	-
30041 ~ 30060 40041 ~ 40060	Temperature readings of port 2 in 0.01°C	-32768 to 32767	R	-
30061 ~ 30080 40061 ~ 40080	Temperature readings of port 3 in 0.01°C	-32768 to 32767	R	-
30081 ~ 30084 40081 ~ 40084	Number of sensors of a port for port 0 to 3.	0 to 20	R	-
30097 ~ 30100 40097 ~ 40100	Number of not assigned sensors of a port for port 0 to 3.	0 to 20	R	-
30113 ~ 30116 40113 ~ 40116	Number of removed sensors of a port for port 0 to 3.	0 to 20	R	-
30129 ~ 30132 40129 ~ 40132	Number of scanned sensors of a port for port 0 to 3.	0 to 20	R	-
30145 ~ 30148 40145 ~ 40148	Number of error counts of a port for port 0 to 3.	0 to 65535	R	-
30161 ~ 30240 40161 ~ 40240	Serial number of sensors of port 0, 4 registers for a sensor	0x0000 to 0xFFFF	R	-
30241 ~ 30320 40241 ~ 40320	Serial number of sensors of port 1, 4 registers for a sensor	0x0000 to 0xFFFF	R	-

30321 ~ 30400 40321 ~ 40400	Serial number of sensors of port 2, 4 registers for a sensor	0x0000 to 0xFFFF	R	-
30401 ~ 30480 40401 ~ 40480	Serial number of sensors of port 3, 4 registers for a sensor	0x0000 to 0xFFFF	R	-
40481	Firmware version (low word)	0x000z for xy.z	R	-
40482	Firmware version (high word)	0x0x0y for xy.z	R	-
40483	Module name (low word)	0x0400	R	0x0400
40484	Module name (high word)	0x0070	R	0x0070
40485	RS-485 module address, 1 to 247 Only for Modbus RTU protocol	1 to 247	R/W	1
40486	RS-485 baud rate and parity settings Bits 5:0 Baud rate, valid range: 3 ~ 10 Bits 7:6 00: no parity, 1 stop bit 01: no parity, 2 stop bit 02: even parity, 1 stop bit 03: odd parity, 1 stop bit	Bits 5:0, baud rate 03: 1200 04: 2400 05: 4800 06: 9600 07: 19200 08: 38400 09: 57600 0A: 115200 Bits 7:6, parity 00: N81 01: N82 02: E81 03: O81	R/W	6
40488	RS-485 response delay time in ms, valid range, 0 ~ 30	0 to 30	R/W	0
40489	RS-485 host watchdog timeout value, 0 ~ 255, in 0.1s	0 to 255	R/W	255
40492	RS-485 host watchdog timeout count, write 0 to clear	0 to 65535	R/W	-
40513 ~ 40532	Assign channel index to a new sensor in the new list of port 0	0 to 19	W	-
40533 ~ 40552	Assign channel index to a new sensor in the new list of port 1	0 to 19	W	-
40553 ~ 40572	Assign channel index to a new sensor in the new list of port 2	0 to 19	W	-
40573 ~ 40592	Assign channel index to a new sensor in the new list of port 3	0 to 19	W	-
30593 ~ 30612 40593 ~ 40612	High latched Temperature readings of port 0 in 0.01°C	-32768 to 32767	R	-

30613 ~ 30632 40613 ~ 40632	High latched Temperature readings of port 1 in 0.01°C	-32768 to 32767	R	-
30633 ~ 30652 40633 ~ 40652	High latched Temperature readings of port 2 in 0.01°C	-32768 to 32767	R	-
30653 ~ 30672 40653 ~ 40672	High latched Temperature readings of port 3 in 0.01°C	-32768 to 32767	R	-
30673 ~ 30692 40673 ~ 40692	Low latched Temperature readings of port 0 in 0.01°C	-32768 to 32767	R	-
30693 ~ 30712 40693 ~ 40712	Low latched Temperature readings of port 1 in 0.01°C	-32768 to 32767	R	-
30713 ~ 30732 40713 ~ 40732	Low latched Temperature readings of port 2 in 0.01°C	-32768 to 32767	R	-
30733 ~ 30752 40733 ~ 40752	Low latched Temperature readings of port 3 in 0.01°C	-32768 to 32767	R	-
30753 ~ 30832 40753 ~ 40832	Serial number of not assigned sensors of port 0, 4 registers for a sensor	0x0000 to 0xFFFF	R	-
30833 ~ 30912 40833 ~ 40912	Serial number of not assigned sensors of port 1, 4 registers for a sensor	0x0000 to 0xFFFF	R	-
30913 ~ 30992 40913 ~ 40992	Serial number of not assigned sensors of port 2, 4 registers for a sensor	0x0000 to 0xFFFF	R	-
30993 ~ 31072 40993 ~ 41072	Serial number of not assigned sensors of port 3, 4 registers for a sensor	0x0000 to 0xFFFF	R	-

31073 ~ 31152 41073 ~ 41152	Serial number of removed sensors of port 0, 4 registers for a sensor	0x0000 to 0xFFFF	R	-
31153 ~ 31232 41153 ~ 41232	Serial number of removed sensors of port 0, 4 registers for a sensor	0x0000 to 0xFFFF	R	-
31233 ~ 31312 41233 ~ 41312	Serial number of removed sensors of port 0, 4 registers for a sensor	0x0000 to 0xFFFF	R	-
31313 ~ 31392 41313 ~ 41392	Serial number of removed sensors of port 0, 4 registers for a sensor	0x0000 to 0xFFFF	R	-
00001 ~ 00004	Write 1 to rescan sensors on a port for port 0 to 3.	1: rescan	W	-
00033 ~ 00052	Write 1 to remove the channel index of a sensor for port 0	1: remove	W	-
00053 ~ 00072	Write 1 to remove the channel index of a sensor for port 1	1: remove	W	-
00073 ~ 00092	Write 1 to remove the channel index of a sensor for port 2	1: remove	W	-
00093 ~ 00112	Write 1 to remove the channel index of a sensor for port 3	1: remove	W	-
00129 ~ 00132	Write 1 to clear all high latched temperature readings of a port for port 0 to 3	1: clear	W	-
00161 ~ 00164	Write 1 to clear all low latched temperature readings of a port for port 0 to 3	1: clear	W	-
00257	RS-485 Protocol, 0: DCON, 1: Modbus RTU Only for Modbus RTU protocol	0: DCON 1: Modbus RTU	R/W	1
00260	Modbus RTU host watchdog mode 0: same as I-7000 (old mode) 1: can use AO and DO command to clear host watchdog timeout status (new mode) Only for Modbus RTU protocol	0: old mode 1: new mode	R/W	0
00261	RS-485 host watchdog mode, 1: enable, 0: disable. Only for Modbus RTU protocol	0: disable 1: enable	R/W	0
00270	Host watch dog timeout status, write 1 to clear host watch dog timeout status (Only for Modbus RTU protocol)	0: normal 1: host watchdog timeout	R/W	-
00273	Reset status, 1: first read after powered on, 0: not the first read after powered on	0: not reset 1: reset	R	-
00280	Write 1 to clear all high latched temperature readings	1: clear	W	-

00281	Write 1 to clear all low latched temperature readings	1: clear	W	-
00385 ~ 00404	Write 1 to clear high latched temperature reading of a sensor of port 0	1: clear	W	-
00405 ~ 00424	Write 1 to clear high latched temperature reading of a sensor of port 1	1: clear	W	-
00425 ~ 00444	Write 1 to clear high latched temperature reading of a sensor of port 2	1: clear	W	-
00445 ~ 00464	Write 1 to clear high latched temperature reading of a sensor of port 3	1: clear	W	-
00465 ~ 00484	Write 1 to clear low latched temperature reading of a sensor of port 0	1: clear	W	-
00485 ~ 00504	Write 1 to clear low latched temperature reading of a sensor of port 1	1: clear	W	-
00505 ~ 00524	Write 1 to clear low latched temperature reading of a sensor of port 2	1: clear	W	-
00525 ~ 00544	Write 1 to clear low latched temperature reading of a sensor of port 3	1: clear	W	-

M-7005

Address	Description	Data Format	Attribute	Factory Default
00001 ~ 00006	Digital output value of channel 0 to 5	0: off 1: on	R/W	-
00097 ~ 00102	Safe value of digital output channel 0 to 5	0: off 1: on	R/W	0
00193 ~ 00198	Power-on value of digital output channel 0 to 5	0: off 1: on	R/W	0
00257	Protocol, 0: DCON, 1: Modbus RTU	0: DCON 1: Modbus RTU	R/W	1
00260	Modbus host watchdog mode 0: same as I-7000 (old mode) 1: can use AO and DO command to clear host watchdog timeout status (new mode)	0: old mode 1: new mode	R/W	0
00261	1: enable, 0: disable host watchdog	0: disable 1: enable	R/W	0
00267	Temperature scale, 1: Celsius, 0: Fahrenheit	0: Fahrenheit 1: Celsius	R/W	1
00269	Modbus data format, 0: hex, 1: engineering	0: hex 1: engineering	R/W	1
00270	Host watch dog timeout status, write 1 to clear host watch dog timeout status	0: normal 1: host watchdog timeout	R/W	-
00272	Write 1 to reload factory calibration parameters	1: reload	W	-
00273	Reset status, 1: first read after powered on, 0: not the first read after powered on	0: not reset 1: reset	R	-
00289 ~ 00296	Write 1 to clear low latched alarm of channel 0 to 7	1: clear	W	-
00305 ~ 00312	Write 1 to clear high latched alarm of channel 0 to 7	1: clear	W	-
00321 ~ 00328	Enable/disable high alarm of channel 0 to 7	0: disable 1: enable	R/W	0
00329 ~ 00336	Enable/disable low alarm of channel 0 to 7	0: disable 1: enable	R/W	0
00337 ~ 00344	High alarm type of channel 0 to 7	0: momentary 1: latched	R/W	0
00345 ~ 00352	Low alarm type of channel 0 to 7	0: momentary 1: latched	R/W	0
10129 ~ 10136 00129 ~ 00136	Over/under range status of channel 0 to 7	0: normal 1: over/under	R	-

30001 ~ 30008 40001 ~ 40008	Analog input value of channel 0 to 7	-32768 to 32767	R	-																				
40225 ~ 40232	High alarm limit of analog input channel 0 to 7	-32768 to 32767	R/W	32767																				
40233 ~ 40240	Low alarm limit of analog input channel 0 to 7	-32768 to 32767	R/W	-32768																				
40257 ~ 40262	Type code of channel 0 to 7 0x60: PreCon Type III 10K@25°C, -30°F ~ 240°F 0x61: Fenwell Type U 2K@25°C, -50°C ~ 150°C 0x62: Fenwell Type U 2K@25°C, 0°C ~ 150°C 0x63: YSI L Mix 100@25°C, -80°C ~ 100°C 0x64: YSI L Mix 300@25°C, -80°C ~ 100°C 0x65: YSI L Mix 1000@25°C, -70°C ~ 100°C 0x66: YSI B Mix 2252@25°C, -50°C ~ 150°C 0x67: YSI B Mix 3000@25°C, -40°C ~ 150°C 0x68: YSI B Mix 5000@25°C, -40°C ~ 150°C 0x69: YSI B Mix 6000@25°C, -30°C ~ 150°C 0x6A: YSI B Mix 10000@25°C, -30°C ~ 150°C 0x6B: YSI H Mix 10000@25°C, -30°C ~ 150°C 0x6C: YSI H Mix 30000@25°C, -10°C ~ 200°C 0x70 to 0x77: User-defined, -50°C ~ 150°C	Refer to description	R/W	0x60																				
40289 ~ 40294	Temperature offset of analog input channel 0 to 7 in 0.1°C, valid range: -128 ~ 127	-128 to 127	R/W	0																				
40321 ~ 40328	High alarm DO port of analog input channel 0 to 7	0 to 5	R/W	0																				
40329 ~ 40336	Low alarm DO port of analog input channel 0 to 7	0 to 5	R/W	0																				
40385 ~ 40390	Resistance offset of channel 0 to 7 in 0.1 ohms, valid range: 0 ~ 255	0 to 255	R/W	0																				
40481	Firmware version (low word)	0x000z for xy.z	R	-																				
40482	Firmware version (high word)	0x0x0y for xy.z	R	-																				
40483	Module name (low word)	0x0500	R	0x0500																				
40484	Module name (high word)	0x0070	R	0x0070																				
40485	Module address, valid range: 1 ~ 247	1 to 247	R/W	1																				
40486	Bits 5:0 Baud rate, 0x03 ~ 0x0A <table border="1" style="margin-left: 20px;"> <tr> <td>Code</td> <td>0x03</td> <td>0x04</td> <td>0x05</td> <td>0x06</td> </tr> <tr> <td>Baud</td> <td>1200</td> <td>2400</td> <td>4800</td> <td>9600</td> </tr> <tr> <td>Code</td> <td>0x07</td> <td>0x08</td> <td>0x09</td> <td>0x0A</td> </tr> <tr> <td>Baud</td> <td>19200</td> <td>38400</td> <td>57600</td> <td>115200</td> </tr> </table> Bits 7:6 00: no parity, 1 stop bit	Code	0x03	0x04	0x05	0x06	Baud	1200	2400	4800	9600	Code	0x07	0x08	0x09	0x0A	Baud	19200	38400	57600	115200	Bits 5:0, baud rate 03: 1200 04: 2400 05: 4800 06: 9600 07: 19200 08: 38400	R/W	6
Code	0x03	0x04	0x05	0x06																				
Baud	1200	2400	4800	9600																				
Code	0x07	0x08	0x09	0x0A																				
Baud	19200	38400	57600	115200																				

	01: no parity, 2 stop bits 02: even parity, 1 stop bit 03: odd parity, 1 stop bit	09: 57600 0A: 115200 Bits 7:6, parity 00: N81 01: N82 02: E81 03: O81		
40488	Modbus response delay time in ms, valid range: 0 ~ 30	0 to 30	R/W	0
40489	Host watchdog timeout value, 0 ~ 255, in 0.1s	0 to 255	R/W	255
40490	Enable/disable analog input channel, bit 0 for channel 0, bit 1 for channel 1, etc. 0 to disable and 1 to enable.	0 to 255	R/W	255
40492	Host watchdog timeout count, write 0 to clear	0 to 65535	R/W	-
40513 ~ 40520	Steinhart Coefficient A of type code 70 to 77	0x0000 to 0xFFFF	R/W	-
40545 ~ 40552	Steinhart Coefficient B of type code 70 to 77	0x0000 to 0xFFFF	R/W	-
40577 ~ 40584	Steinhart Coefficient C of type code 70 to 77	0x0000 to 0xFFFF	R/W	-
30865 ~ 30880 40865 ~ 40880	Resistance value of analog input channel 0 to 7 in 0.1 ohm, two registers for each channel. For firmware version A5.3 and later.	0 to 65535	R	-

M-7011

Address	Description	Data Format	Attribute	Factory Default
30001 40001	Analog input value of channel 0	-32768 to 32767	R	-
30129 40129	CJC temperature in 0.01C	-5000 to 10000	R	-
30097 40097	Counter value of DI 0	0 to 65535	R	-
40225 ~ 40226	Low/high analog input alarm limits	-32768 to 32767	R/W	-
40481	Firmware version (low word)	0x0000	R	0x0000
40482	Firmware version (high word)	0xab0c for ab.c	R	-
40483	Module name (low word)	0x1100	R	0x1100
40484	Module name (high word)	0x0070	R	0x0070
40485	Module address	1 to 247	R/W	1
40486	Baud rate	Bits 5:0, baud rate 03: 1200 04: 2400 05: 4800 06: 9600 07: 19200 08: 38400 09: 57600 0A: 115200 Bits 7:6, parity 00: N81 01: N82 02: E81 03: O81	R/W	6
40487	Type code 0x00: ±15 mV 0x01: ±50 mV 0x02: ±100 mV 0x03: ±500 mV 0x04: ±1 V 0x05: ±2.5 V 0x06: ±20 mA 0x0E: type J thermocouple 0x0F: type K thermocouple 0x10: type T thermocouple 0x11: type E thermocouple 0x12: type R thermocouple	Refer to description	R/W	5

	0x13: type S thermocouple 0x14: type B thermocouple 0x15: type N thermocouple 0x16: type C thermocouple 0x17: type L thermocouple 0x18: type M thermocouple			
40488	Modbus response delay time in ms	0 to 30	R/W	0
40489	Host watchdog timeout value, 0 ~ 255, in 0.1s	0 to 255	R/W	255
40491	Module CJC offset in 0.01C	-4096 to 4096	R/W	0
40492	Host watchdog timeout count, write 0 to clear	0 to 65535	R/W	-
40495	LED mode, 1: controlled by module, 2: controlled by host (for M-7011D only)	1: by module 2: by host	R/W	1
40496	LED data for host control mode, valid ranges: -19999 ~ + 19999 (for M-7011D only)	-19999 to 19999	W	-
10001 00001	Digital input channel 0	0: off 1: on	R	-
10129 00129	1: thermocouple open wire	0: normal 1: open	R	-
00033	Digital outputs	0: off 1: on	R/W	-
00097	Safe values of digital outputs	0: off 1: on	R/W	0
00193	Power on values of digital outputs	0: off 1: on	R/W	0
00257	Protocol, 0: DCON, 1: Modbus RTU	0: DCON 1: Modbus RTU	R/W	1
00259	Filter setting, 0: 60Hz rejection, 1: 50Hz rejection	0: 60Hz rejection 1: 50Hz rejection	R/W	0
00260	Modbus host watchdog mode 0: same as I-7000 (old mode) 1: can use AO and DO command to clear host watchdog timeout status (new mode)	0: old mode 1: new mode	R/W	0
00261	1: enable, 0: disable host watchdog	0: disable 1; enable	R/W	0
00262	1: enable, 0: disable alarm	0: disable 1: enable	R/W	0
00263	1: latch, 0: momentary alarm	0: momentary 1: latch	R/W	0
00264	1: clear latch alarm	1: clear	W	-
00266	1: clear counter	1: clear	W	-
00268	1: enable, 0: disable CJC offset	0: disable 1: enable	R/W	1

00269	Modbus data format, 0: hex, 1: engineering	0: hex 1: engineering	R/W	0
00270	Host watch dog timeout status, write 1 to clear host watch dog timeout status	0: normal 1: host watchdog timeout	R/W	-
00273	Reset status, 1: first read after power d on, 0: not the first read after powered on	0: not reset 1; reset	R	-
00276	Open wire detection, 1: enable, 0: disable	0: disable 1; enable	R/W	1

M-7013P

Address	Description	Data Format	Attribute	Factory Default
30001	Analog input value of channel 0	-32768 to 32767 (0x8000 to 0x7FFF)	R	-
30097	Counter value of DI 0	0 to 65535	R	-
40225 ~ 40226	Low/high analog input alarm limit	-32768 to 32767 (0x8000 to 0x7FFF)	R/W	-
40481	Firmware version (low word)	0x0000	R	0x0000
40482	Firmware version (high word)	0xab0c for ab.c	R	-
40483	Module name (low word)	0x1320	R	0x1320
40484	Module name (high word)	0x0070	R	0x0070
40485	Module address	1 to 247	R/W	1
40486	Baud rate	Bits 5:0, baud rate 03: 1200 04: 2400 05: 4800 06: 9600 07: 19200 08: 38400 09: 57600 0A: 115200 Bits 7:6, parity 00: N81 01: N82 02: E81 03: O81	R/W	6
40487	Type code 0x20: Pt 100, $\alpha=0.00385$, -100 ~ 100°C 0x21: Pt 100, $\alpha=0.00385$, 0 ~ 100°C 0x22: Pt 100, $\alpha=0.00385$, 0 ~ 200°C 0x23: Pt 100, $\alpha=0.00385$, 0 ~ 600°C 0x24: Pt 100, $\alpha=0.003916$, -100 ~ 100°C 0x25: Pt 100, $\alpha=0.003916$, 0 ~ 100°C 0x26: Pt 100, $\alpha=0.003916$, 0 ~ 200°C 0x27: Pt 100, $\alpha=0.003916$, 0 ~ 600°C 0x28: Ni 120, -80 ~ 100°C 0x29: Ni 120, 0 ~ 100°C 0x2A: Pt 1000, $\alpha=0.00385$, -200 ~ 600°C 0x2E: Pt 100, $\alpha=0.00385$, -200 ~ 200°C 0x2F: Pt 100, $\alpha=0.003916$, -200 ~ 200°C 0x80: Pt 100, $\alpha=0.00385$, -200 ~ 600°C 0x81: Pt 100, $\alpha=0.003916$, -200 ~ 600°C	Refer to description	R/W	020

Address	Description	Data Format	Attribute	Factory Default
40488	Modbus response delay time in ms	0 to 30	R/W	0
40489	Host watchdog timeout value, 0 ~ 255, in 0.1s	0 to 255	R/W	255
40492	Host watchdog timeout count, write 0 to clear	0 to 65535	R/W	-
40495	LED mode, 1: controlled by module, 2: controlled by host (for M-7011D only)	1: by module 2: by host	R/W	1
40496	LED data for host control mode, valid ranges: -19999 ~ + 19999 (for M-7011D only)	-19999 to 19999	W	-
30865	Low word of resistance value of analog input channel 0 in 0.01 ohm	0 to 65535	R	-
30866	High word of resistance value of analog input channel 0 in 0.01 ohm	0 to 65535	R	-
10001	Digital input channel 0	0: off 1: on	R	-
00033 ~	Digital outputs	0: off 1: on	R/W	-
00097 ~	Safe values of digital outputs	0: off 1: on	R/W	0
00193 ~	Power on values of digital outputs	0: off 1: on	R/W	0
00257	Protocol, 0: DCON, 1: Modbus RTU	0: DCON 1: Modbus RTU	R/W	1
00259	Filter setting, 0: 60Hz rejection, 1: 50Hz rejection	0: 60Hz rejection 1: 50Hz rejection	R/W	0
00260	Modbus host watchdog mode 0: same as I-7000 (old mode) 1: can use AO and DO command to clear host watchdog timeout status (new mode)	0: old mode 1: new mode	R/W	0
00261	1: enable, 0: disable host watchdog	0: disable 1: enable	R/W	0
00262	1: enable, 0: disable analog input alarm	0: disable 1: enable	R/W	0
00263	1: latch, 0: momentary analog input alarm	0: momentary 1: latch	R/W	0
00264	1: clear latched analog input alarm	1: clear	W	-
00266	1: clear counter	1: clear	W	-
00269	Modbus data format, 0: hex, 1: engineering	0: hex 1: engineering	R/W	1
00270	Host watch dog timeout status, write 1 to clear host watch dog timeout status	0: normal 1: host watchdog timeout	R/W	-

Address	Description	Data Format	Attribute	Factory Default
00273	Reset status, 1: first read after power d on, 0: not the first read after powered on	0: not reset 1: reset	R	-

M-7015/M-7015P

(firmware version B202 and later)

Address	Description	Data Format	Attribute	Factory Default
10129 ~ 10134 00129 ~ 00134	Over/under range status of channel 0 to 5	0: normal 1: over/under	R	-
30001 ~ 30006 40001 ~ 40006	Analog input value of channel 0 to 5	-32768 to 32767 (0x8000 to 0x7FFF)	R	-
40257 ~ 40262	Type code of channel 0 to 5 0x20: Pt 100, $\alpha=0.00385$, $-100 \sim 100^{\circ}\text{C}$ 0x21: Pt 100, $\alpha=0.00385$, $0 \sim 100^{\circ}\text{C}$ 0x22: Pt 100, $\alpha=0.00385$, $0 \sim 200^{\circ}\text{C}$ 0x23: Pt 100, $\alpha=0.00385$, $0 \sim 600^{\circ}\text{C}$ 0x24: Pt 100, $\alpha=0.003916$, $-100 \sim 100^{\circ}\text{C}$ 0x25: Pt 100, $\alpha=0.003916$, $0 \sim 100^{\circ}\text{C}$ 0x26: Pt 100, $\alpha=0.003916$, $0 \sim 200^{\circ}\text{C}$ 0x27: Pt 100, $\alpha=0.003916$, $0 \sim 600^{\circ}\text{C}$ 0x28: Ni 120, $-80 \sim 100^{\circ}\text{C}$ 0x29: Ni 120, $0 \sim 100^{\circ}\text{C}$ 0x2A: Pt 1000, $\alpha=0.00385$, $-200 \sim 600^{\circ}\text{C}$ 0x2B: Cu 100, $\alpha=0.00421$, $-20 \sim 150^{\circ}\text{C}$ 0x2C: Cu 100, $\alpha=0.00427$, $0 \sim 200^{\circ}\text{C}$ 0x2D: Cu 1000, $\alpha=0.00421$, $-20 \sim 150^{\circ}\text{C}$ 0x2E: Pt 100, $\alpha=0.00385$, $-200 \sim 200^{\circ}\text{C}$ 0x2F: Pt 100, $\alpha=0.003916$, $-200 \sim 200^{\circ}\text{C}$ 0x80: Pt 100, $\alpha=0.00385$, $-200 \sim 600^{\circ}\text{C}$ 0x81: Pt 100, $\alpha=0.003916$, $-200 \sim 600^{\circ}\text{C}$ 0x82: Cu 50 @ 0°C , $-50 \sim 150^{\circ}\text{C}$ 0x83: Ni 100, $-60 \sim 180^{\circ}\text{C}$ 0x84: Ni 120, $-80 \sim 150^{\circ}\text{C}$ 0x85: Cu 100, $\alpha=0.00428$, $0 \sim 150^{\circ}\text{C}$	Refer to description	R/W	0x20
40289 ~ 40294	Temperature offset of channel 0 to 5 in 0.1°C , valid range: $-128 \sim 127$	-128 to 127	R/W	0
40385 ~ 40390	Resistance offset of channel 0 to 5 in 0.1 ohms, valid range: $0 \sim 255$	0 to 255	R/W	0
40481	Firmware version (low word)	0x0000	R	0x0000
40482	Firmware version (high word)	0xab0c for ab.c	R	-
40483	Module name (low word)	0x1500	R	0x1500
40484	Module name (high word)	0x0070	R	0x0070

Address	Description	Data Format	Attribute	Factory Default				
40485	Module address, valid range: 1 ~ 247	1 to 247	R/W	1				
40486	Bits 5:0 Baud rate, 0x03 ~ 0x0A	Refer description to	R/W	6				
	Code				0x03	0x04	0x05	0x06
	Baud				1200	2400	4800	9600
	Code				0x07	0x08	0x09	0x0A
	Baud	19200	38400	57600	115200			
	Bits 7:6 00: no parity, 1 stop bit 01: no parity, 2 stop bits 02: even parity, 1 stop bit 03: odd parity, 1 stop bit							
40488	Modbus response delay time in ms	0 to 30	R/W	0				
40489	Host watchdog timeout value, 0 ~ 255, in 0.1s	0 to 255	R/W	255				
40490	Enable/disable analog input channel, bit 0 for channel 0, bit 1 for channel 1, etc. 0 to disable and 1 to enable.	0 to 63	R/W	63				
40492	Host watchdog timeout count, write 0 to clear	0 to 65535	R/W	-				
00257	Protocol, 0: DCON, 1: Modbus RTU	0: DCON 1: Modbus RTU	R/W	1				
00259	Filter setting, 0: 60Hz rejection, 1: 50Hz rejection	0: 60Hz rejection 1: 50Hz rejection	R/W	0				
00260	Modbus host watchdog mode 0: same as I-7000 (old mode) 1: can use AO and DO command to clear host watchdog timeout status (new mode)	0: old mode 1: new mode	R/W	0				
00261	1: enable, 0: disable host watchdog	0: disable 1; enable	R/W	0				
00269	Modbus data format, 0: hex, 1: engineering	0: hex 1; engineering	R/W	1				
00270	Host watch dog timeout status, write 1 to clear host watch dog timeout status	0: normal 1: host watchdog timeout	R/W	-				
00272	Write 1 to reload factory calibration parameters	1: reload	W	-				
00273	Reset status, 1: first read after powered on, 0: not the first read after powered on	0: not reset 1: reset	R	-				
00275	1: force to return 32767 for wire opening	0: -32768/32767 for open 1: 32767 for open	R/W	-				

Notes:

1. The max number of analog output registers written in a command is 11.

2. The command of loading factory calibration parameters takes about 3 seconds. The next command should be sent after 3 seconds.

M-7016

Address	Description	Data Format	Attribute	Factory Default
30001 40001	Analog input value of channel 0	-32768 to 32767 (0x8000 to 0x7FFF)	R	-
30002 40002	Analog input value of channel 1	-32768 to 32767 (0x8000 to 0x7FFF)	R	-
30097 40097	Counter value of digital input	0 to 65535	R	-
40033	Output value of excitation voltage, 0 ~ 10000	0 to 10000	R/W	-
40193	Power on value of excitation voltage, 0 ~ 10000	0 to 10000	R/W	-
00001	Digital input value of channel 0	0: Off 1: On	R	-
00033	Digital output value of channel 0	0: Off 1: On	R/W	-
00034	Digital output value of channel 1	0: Off 1: On	R/W	-
00035	Digital output value of channel 2	0: Off 1: On	R/W	-
00036	Digital output value of channel 3	0: Off 1: On	R/W	-
00097	Safe value of digital output channel 0	0: Off 1: On	R/W	0
00098	Safe value of digital output channel 1	0: Off 1: On	R/W	0
00099	Safe value of digital output channel 2	0: Off 1: On	R/W	0
00100	Safe value of digital output channel 3	0: Off 1: On	R/W	0
00193	Power on value of digital output channel 0	0: Off 1: On	R/W	0
00194	Power on value of digital output channel 1	0: Off 1: On	R/W	0
00195	Power on value of digital output channel 2	0: Off 1: On	R/W	0
00196	Power on value of digital output channel 3	0: Off 1: On	R/W	0
40161	S1 value of linear mapping	-32768 to 32767	R/W	-
40162	S2 value of linear mapping	-32768 to 32767	R/W	-
40163	T1 value of linear mapping	-32768 to 32767	R/W	-
40164	T2 value of linear mapping	-32768 to 32767	R/W	-

Address	Description	Data Format	Attribute	Factory Default
40225	Low limit of analog input alarm value	-32768 to 32767	R/W	-32768
40226	High limit of analog input alarm value	-32768 to 32767	R/W	32767
40481	Firmware version (low word)	0x0000	R	0x0000
40482	Firmware version (high word)	0xab0c for ab.c	R	-
40483	Module name (low word)	0x1600	R	0x1600
40484	Module name (high word)	0x0070	R	0x0070
40485	Module address (1 ~ 247)	1 to 247	R/W	1
40486	Baud rate (3 ~ 10)	Bits 5:0, baud rate 03: 1200 04: 2400 05: 4800 06: 9600 07: 19200 08: 38400 09: 57600 0A: 115200 Bits 7:6, parity 00: N81 01: N82 02: E81 03: O81	R/W	6
40487	Type code (0 ~ 6)	0x00: ±15 mV 0x01: ±50 mV 0x02: ±100 mV 0x03: ±500 mV 0x04: ±1 V 0x05: ±2.5 V 0x06: ±20 mA	R/W	5
40488	Response delay time (0 ~ 30)	0 to 30	R/W	0
40489	Host watchdog timeout time in 100ms (0 ~ 255)	0 to 255	R/W	255
40490	Analog input channel mode, 0: channel 0, 1: channel 1, 2: 2-channel mode	0: channel 0 1: channel 1 2: 2-channel	R/W	0
40492	Host watchdog timeout count, write 0 to clear	0 to 65535	R/W	-
40495	LED control mode, 1: module, 2: host	1: by module 2: by host	R/W	1
40496	LED data in host control mode, -19999 ~ +19999, read as 0	-19999 to 19999	W	-

Address	Description	Data Format	Attribute	Factory Default
00257	Protocol selection, 0: DCON, 1: Modbus RTU	0: DCON 1: Modbus RTU	R/W	1
00259	Filter setting, 0: 60Hz rejection, 1: 50Hz rejection	0: 60Hz rejection 1: 50Hz rejection	R/W	0
00260	Modbus host watchdog mode 0: same as I-7000 (old mode) 1: can use AO and DO command to clear host watchdog timeout status (new mode)	0: old mode 1: new mode	R/W	0
00261	Host watchdog, 0: disable, 1: enable	0: disable 1: enable	R/W	0
00262	Analog input alarm, 0: disable, 1: enable	0: disable 1: enable	R/W	0
00263	Analog input alarm type, 0: momentary, 1: latched	0: momentary 1: latched	R/W	0
00264	1 to clear latched alarm	1: clear	W	-
00265	Linear mapping, 0: disable, 1: enable	0: disable 1: enable	R/W	0
00266	1 to clear counter	1: clear	W	-
00269	Modbus data format, 0: hex, 1: engineering	0: hex 1: engineering	R/W	0
00270	Host watchdog timeout status, write 1 to clear host watch dog timeout status	0: normal 1: host watchdog timeout	R/W	-
00273	Reset status, 1: first read after powered on, 0: not the first read after powered on	0: not reset 1: reset	R	-

M-7017/M-7017R

(firmware version B300 and later)

Address	Description	Data Format	Attribute	Factory Default																				
10129 ~ 10136 00129 ~ 00136	Under range status of channel 0 to 7 for 4 ~ 20mA or 0 ~ 20mA ranges	0: normal 1: under	R	-																				
30001 ~ 30008 40001 ~ 40008	Analog input value of channel 0 to 7	-32768 to 32767 (0x8000 to 0x7FFF)	R	-																				
40481	Firmware version (low word)	0x0000	R	0x0000																				
40482	Firmware version (high word)	0xab0c for ab.c	R	-																				
40483	Module name (low word)	0x1700 for 17 0x1722 for 17R	R	-																				
40484	Module name (high word)	0x0070	R	0x0070																				
40485	Module address, valid range: 1 ~ 247	1 to 247	R/W	1																				
40486	Bits 5:0 Baud rate, 0x03 ~ 0x0A <table border="1" style="margin-left: 20px;"> <tbody> <tr> <td>Code</td> <td>0x03</td> <td>0x04</td> <td>0x05</td> <td>0x06</td> </tr> <tr> <td>Baud</td> <td>1200</td> <td>2400</td> <td>4800</td> <td>9600</td> </tr> <tr> <td>Code</td> <td>0x07</td> <td>0x08</td> <td>0x09</td> <td>0x0A</td> </tr> <tr> <td>Baud</td> <td>19200</td> <td>38400</td> <td>57600</td> <td>115200</td> </tr> </tbody> </table> Bits 7:6 00: no parity, 1 stop bit 01: no parity, 2 stop bits 02: even parity, 1 stop bit 03: odd parity, 1 stop bit	Code	0x03	0x04	0x05	0x06	Baud	1200	2400	4800	9600	Code	0x07	0x08	0x09	0x0A	Baud	19200	38400	57600	115200	Refer to description	R/W	6
Code	0x03	0x04	0x05	0x06																				
Baud	1200	2400	4800	9600																				
Code	0x07	0x08	0x09	0x0A																				
Baud	19200	38400	57600	115200																				
40487	Type code	0x07: 4 ~ 20 mA 0x08: ±10 V 0x09: ±5 V 0x0A: ±1 V 0x0B: ±500 mV 0x0C: ±150 mV 0x0D: ±20 mA 0x1A: 0 ~ 20 mA	R/W	8																				
40488	Modbus response delay time in ms	0 to 30	R/W	0																				
40489	Host watchdog timeout value, 0 ~ 255, in 0.1s	0 to 255	R/W	255																				
40490	Enable/disable analog input channel, bit 0 for channel 0, bit 1 for channel 1, etc. 0 to disable and 1 to enable.	0 to 255	R/W	255																				
40492	Host watchdog timeout count, write 0 to clear	0 to 65535	R/W	-																				

00257	Protocol, 0: DCON, 1: Modbus RTU	0: DCON 1: Modbus RTU	R/W	1
00259	Filter setting, 0: 60Hz rejection, 1: 50Hz rejection	0: 60Hz rejection 1: 50Hz rejection	R/W	0
00261	1: enable, 0: disable host watchdog	0: disable 1: enable	R/W	0
00269	Modbus data format, 0: hex, 1: engineering	0: hex 1: engineering	R/W	0
00270	Host watch dog timeout status, write 1 to clear host watch dog timeout status	0: normal 1: host watchdog timeout	R/W	-
00271	1: enable, 0: disable fast mode, only for M-7017R	0: disable 1: enable	R/W	0
00273	Reset status, 1: first read after powered on, 0: not the first read after powered on	0: not reset 1: reset	R	-

M-7017C/M-7017RC

(firmware version B300 and later)

Address	Description	Data Format	Attribute	Factory Default																				
10129 ~ 10136 00129 ~ 00136	Under range status of channel 0 to 7 for 4 ~ 20mA or 0 ~ 20mA ranges	0: normal 1: under	R	-																				
30001 ~ 30008 40001 ~ 40008	Analog input value of channel 0 to 7	-32768 to 32767 (0x8000 to 0x7FFF)	R	-																				
40481	Firmware version (low word)	0x0000	R	0x0000																				
40482	Firmware version (high word)	0xab0c for ab.c	R	-																				
40483	Module name (low word)	0x1713 for 17C 0x1732 for 17RC	R	-																				
40484	Module name (high word)	0x0070	R	0x0070																				
40485	Module address, valid range: 1 ~ 247	1 to 247	R/W	1																				
40486	Bits 5:0 Baud rate, 0x03 ~ 0x0A <table border="1" style="margin-left: 20px;"> <tbody> <tr> <td>Code</td> <td>0x03</td> <td>0x04</td> <td>0x05</td> <td>0x06</td> </tr> <tr> <td>Baud</td> <td>1200</td> <td>2400</td> <td>4800</td> <td>9600</td> </tr> <tr> <td>Code</td> <td>0x07</td> <td>0x08</td> <td>0x09</td> <td>0x0A</td> </tr> <tr> <td>Baud</td> <td>19200</td> <td>38400</td> <td>57600</td> <td>115200</td> </tr> </tbody> </table> Bits 7:6 00: no parity, 1 stop bit 01: no parity, 2 stop bits 02: even parity, 1 stop bit 03: odd parity, 1 stop bit	Code	0x03	0x04	0x05	0x06	Baud	1200	2400	4800	9600	Code	0x07	0x08	0x09	0x0A	Baud	19200	38400	57600	115200	Refer to description	R/W	6
Code	0x03	0x04	0x05	0x06																				
Baud	1200	2400	4800	9600																				
Code	0x07	0x08	0x09	0x0A																				
Baud	19200	38400	57600	115200																				
40487	Type code	0x07: 4 ~ 20 mA 0x0D: ±20 mA 0x1A: 0 ~ 20 mA	R/W	0x0D																				
40488	Modbus response delay time in ms	0 to 30	R/W	0																				
40489	Host watchdog timeout value, 0 ~ 255, in 0.1s	0 to 255	R/W	255																				
40490	Enable/disable analog input channel, bit 0 for channel 0, bit 1 for channel 1, etc. 0 to disable and 1 to enable.	0 to 255	R/W	255																				
40492	Host watchdog timeout count, write 0 to clear	0 to 65535	R/W	-																				
00257	Protocol, 0: DCON, 1: Modbus RTU	0: DCON 1: Modbus RTU	R/W	1																				
00259	Filter setting, 0: 60Hz rejection, 1: 50Hz rejection	0: 60Hz rejection 1: 50Hz rejection	R/W	0																				

00261	1: enable, 0: disable host watchdog	0: disable 1: enable	R/W	0
00269	Modbus data format, 0: hex, 1: engineering	0: hex 1: engineering	R/W	1
00270	Host watch dog timeout status, write 1 to clear host watch dog timeout status	0: normal 1: host watchdog timeout	R/W	-
00271	1: enable, 0: disable fast mode, only for M-7017RC	0: disable 1: enable	R/W	0
00273	Reset status, 1: first read after powered on, 0: not the first read after powered on	0: not reset 1: reset	R	-

M-7017R-A5

(firmware version B300 and later)

Address	Description	Data Format	Attribute	Factory Default																				
30001 ~ 30008 40001 ~ 40008	Analog input value of channel 0 to 7	-32768 to 32767 (0x8000 to 0x7FFF)	R	-																				
40481	Firmware version (low word)	0x0000	R	0x0000																				
40482	Firmware version (high word)	0xab0c for ab.c	R	-																				
40483	Module name (low word)	0x1731	R	0x1731																				
40484	Module name (high word)	0x0070	R	0x0070																				
40485	Module address, valid range: 1 ~ 247	1 to 247	R/W	1																				
40486	Bits 5:0 Baud rate, 0x03 ~ 0x0A <table border="1" style="margin-left: 20px;"> <tr> <td>Code</td> <td>0x03</td> <td>0x04</td> <td>0x05</td> <td>0x06</td> </tr> <tr> <td>Baud</td> <td>1200</td> <td>2400</td> <td>4800</td> <td>9600</td> </tr> <tr> <td>Code</td> <td>0x07</td> <td>0x08</td> <td>0x09</td> <td>0x0A</td> </tr> <tr> <td>Baud</td> <td>19200</td> <td>38400</td> <td>57600</td> <td>115200</td> </tr> </table> Bits 7:6 00: no parity, 1 stop bit 01: no parity, 2 stop bits 02: even parity, 1 stop bit 03: odd parity, 1 stop bit	Code	0x03	0x04	0x05	0x06	Baud	1200	2400	4800	9600	Code	0x07	0x08	0x09	0x0A	Baud	19200	38400	57600	115200	Refer to description	R/W	6
Code	0x03	0x04	0x05	0x06																				
Baud	1200	2400	4800	9600																				
Code	0x07	0x08	0x09	0x0A																				
Baud	19200	38400	57600	115200																				
40487	Type code	0x1B: ±150V 0x1C: ±50V	R/W	0x1B																				
40488	Modbus response delay time in ms	0 to 30	R/W	0																				
40489	Host watchdog timeout value, 0 ~ 255, in 0.1s	0 to 255	R/W	255																				
40490	Enable/disable analog input channel, bit 0 for channel 0, bit 1 for channel 1, etc. 0 to disable and 1 to enable.	0 to 255	R/W	255																				
40492	Host watchdog timeout count, write 0 to clear	0 to 65535	R/W	-																				
00257	Protocol, 0: DCON, 1: Modbus RTU	0: DCON 1: Modbus RTU	R/W	1																				
00259	Filter setting, 0: 60Hz rejection, 1: 50Hz rejection	0: 60Hz rejection 1: 50Hz rejection	R/W	0																				
00261	1: enable, 0: disable host watchdog	0: disable 1: enable	R/W	0																				
00269	Modbus data format, 0: hex, 1: engineering	0: hex 1: engineering	R/W	0																				

00270	Host watch dog timeout status, write 1 to clear host watch dog timeout status	0: normal 1: host watchdog timeout	R/W	-
00271	1: enable, 0: disable fast mode	0: disable 1: enable	R/W	0
00273	Reset status, 1: first read after powered on, 0: not the first read after powered on	0: not reset 1: reset	R	-

M-7017RMS

Address	Description	Data Format	Attribute	Factory Default																				
30001 ~ 30008 40001 ~ 40008	Analog input value of channel 0 to 7	-32768 to 32767 (0x8000 to 0x7FFF)	R	-																				
40257 ~ 40264	Type code of channel 0 to 7	0x08: ±10 V 0x09: ±5 V 0x0A: ±1 V 0x0B: ±500 mV 0x0C: ±150 mV	R/W	8																				
40481	Firmware version (low word)	0x0000	R	0x0000																				
40482	Firmware version (high word)	0xab0c for ab.c	R	-																				
40483	Module name (low word)	0x173D	R	0x173D																				
40484	Module name (high word)	0x0070	R	0x0070																				
40485	Module address, valid range: 1 ~ 247	1 to 247	R/W	1																				
40486	Bits 5:0 Baud rate, 0x03 ~ 0x0A <table border="1" data-bbox="380 1037 992 1199"> <thead> <tr> <th>Code</th> <th>0x03</th> <th>0x04</th> <th>0x05</th> <th>0x06</th> </tr> </thead> <tbody> <tr> <td>Baud</td> <td>1200</td> <td>2400</td> <td>4800</td> <td>9600</td> </tr> <tr> <th>Code</th> <th>0x07</th> <th>0x08</th> <th>0x09</th> <th>0x0A</th> </tr> <tr> <td>Baud</td> <td>19200</td> <td>38400</td> <td>57600</td> <td>115200</td> </tr> </tbody> </table> Bits 7:6 00: no parity, 1 stop bit 01: no parity, 2 stop bits 02: even parity, 1 stop bit 03: odd parity, 1 stop bit	Code	0x03	0x04	0x05	0x06	Baud	1200	2400	4800	9600	Code	0x07	0x08	0x09	0x0A	Baud	19200	38400	57600	115200	Refer to description	R/W	6
Code	0x03	0x04	0x05	0x06																				
Baud	1200	2400	4800	9600																				
Code	0x07	0x08	0x09	0x0A																				
Baud	19200	38400	57600	115200																				
40488	Modbus response delay time in ms, valid range: 0 ~ 30	0 to 30	R/W	0																				
40489	Host watchdog timeout value, 0 ~ 255, in 0.1s	0 to 255	R/W	255																				
40490	Enable/disable analog input channel, bit 0 for channel 0, bit 1 for channel 1, etc. 0 to disable and 1 to enable.	0 to 255	R/W	255																				
40492	Host watchdog timeout count, write 0 to clear	0 to 65535	R/W	-																				

Address	Description	Data Format	Attribute	Factory Default
00257	Protocol, 0: DCON, 1: Modbus RTU	0: DCON 1: Modbus RTU	R/W	1
00259	Filter setting, 0: 60Hz rejection, 1: 50Hz rejection	0: 60Hz rejection 1: 50Hz rejection	R/W	0
00261	1: enable, 0: disable host watchdog	0: disable 1: enable	R/W	0
00269	Modbus data format, 0: hex, 1: engineering	0: hex 1: engineering	R/W	1
00270	Host watch dog timeout status, write 1 to clear host watch dog timeout status	0: normal 1: host watchdog timeout	R/W	-
00273	Reset status, 1: first read after powered on, 0: not the first read after powered on	0: not reset 1: reset	R	-

M-7017Z

Address	Description	Data Format	Attribute	Factory Default																								
10129 ~ 10138 00129 ~ 00138	Under range status of channel 0 to 9 for 4 ~ 20mA or 0 ~ 20mA ranges	0: normal 1: under	R	-																								
30001 ~ 30020 40001 ~ 40020	Analog input value of channel 0 to 19	-32768 to 32767 (0x8000 to 0x7FFF)	R	-																								
40257 ~ 40276	Type code of channel 0 to 19	0x07: 4 ~ 20 mA 0x08: ±10 V 0x09: ±5 V 0x0A: ±1 V 0x0B: ±500 mV 0x0C: ±150 mV 0x0D: ±20 mA 0x1A: 0 ~ 20 mA	R/W	8																								
40481	Firmware version (low word)	0x0000	R	0x0000																								
40482	Firmware version (high word)	0xab0c for ab.c	R	-																								
40483	Module name (low word)	0x172A	R	0x172A																								
40484	Module name (high word)	0x0070	R	0x0070																								
40485	Module address, valid range: 1 ~ 247	1 to 247	R/W	1																								
40486	Bits 5:0 Baud rate, 0x03 ~ 0x0A <table border="1" style="margin-left: 20px;"> <tr> <td>Code</td> <td>0x03</td> <td>0x04</td> <td>0x05</td> <td>0x06</td> <td></td> </tr> <tr> <td>Baud</td> <td>1200</td> <td>2400</td> <td>4800</td> <td>9600</td> <td></td> </tr> <tr> <td>Code</td> <td>0x07</td> <td>0x08</td> <td>0x09</td> <td>0x0A</td> <td></td> </tr> <tr> <td>Baud</td> <td>19200</td> <td>38400</td> <td>57600</td> <td>115200</td> <td></td> </tr> </table> Bits 7:6 00: no parity, 1 stop bit 01: no parity, 2 stop bits 02: even parity, 1 stop bit 03: odd parity, 1 stop bit	Code	0x03	0x04	0x05	0x06		Baud	1200	2400	4800	9600		Code	0x07	0x08	0x09	0x0A		Baud	19200	38400	57600	115200		Refer to description	R/W	6
Code	0x03	0x04	0x05	0x06																								
Baud	1200	2400	4800	9600																								
Code	0x07	0x08	0x09	0x0A																								
Baud	19200	38400	57600	115200																								
40488	Modbus response delay time in ms	0 to 30	R/W	0																								
40489	Host watchdog timeout value, 0 ~ 255, in 0.1s	0 to 255	R/W	255																								
40490	Enable/disable analog input channel, bit 0 for channel 0, bit 1 for channel 1, etc. 0 to disable and 1 to enable.	0 to 65535	R/W	1023																								
40492	Host watchdog timeout count, write 0 to clear	0 to 65535	R/W	-																								

Address	Description	Data Format	Attribute	Factory Default
40497	Channel enable/disable, high word, LSB for channel 16 and MSB for channel 19.	0 to 15	R/W	0
00257	Protocol, 0: DCON, 1: Modbus RTU	0: DCON 1: Modbus RTU	R/W	1
00259	Filter setting, 0: 60Hz rejection, 1: 50Hz rejection	0: 60Hz rejection 1: 50Hz rejection	R/W	0
00260	Modbus host watchdog mode 0: same as I-7000 (old mode) 1: can use AO and DO command to clear host watchdog timeout status (new mode)	0: old mode 1: new mode	R/W	0
00261	1: enable, 0: disable host watchdog	0: disable 1: enable	R/W	0
00269	Modbus data format, 0: hex, 1: engineering	0: hex 1: engineering	R/W	0
00270	Host watch dog timeout status, write 1 to clear host watch dog timeout status	0: normal 1: host watchdog timeout	R/W	-
00271	1: enable, 0: disable fast mode	0: disable 1: enable	R/W	0
00273	Reset status, 1: first read after powered on, 0: not the first read after powered on	0: not reset 1: reset	R	-
00277	1: single-ended mode, 0: differential mode	0: differential 1: single-ended	R/W	-

M-7018/M-7018R

(firmware version B305 and later)

Address	Description	Data Format	Attribute	Factory Default																				
30001 ~ 30008 40001 ~ 40008	Analog input value of channel 0 to 7	-32768 to 32767 (0x8000 to 0x7FFF)	R	-																				
30129 40129	CJC temperature in 0.01°C	-5000 to 10000	R	-																				
40353 ~ 40360	CJC offset of channel 0 to 7 in 0.1°C. 1 for 0.1, 127 for 12.7, 255 for -0.1, 128 for -12.8	0 to 255	R/W	0																				
40481	Firmware version (low word)	0x0000	R	0x0000																				
40482	Firmware version (high word)		R	-																				
40483	Module name (low word)	0x1800 for 18 0x1822 for 18R	R	-																				
40484	Module name (high word)	0x0070	R	0x0070																				
40485	Module address, valid range: 1 ~ 247	1 to 247	R/W	1																				
40486	Bits 5:0 Baud rate, 0x03 ~ 0x0A <table border="1" data-bbox="360 1045 992 1207"> <thead> <tr> <th>Code</th> <th>0x03</th> <th>0x04</th> <th>0x05</th> <th>0x06</th> </tr> </thead> <tbody> <tr> <td>Baud</td> <td>1200</td> <td>2400</td> <td>4800</td> <td>9600</td> </tr> <tr> <th>Code</th> <th>0x07</th> <th>0x08</th> <th>0x09</th> <th>0x0A</th> </tr> <tr> <td>Baud</td> <td>19200</td> <td>38400</td> <td>57600</td> <td>115200</td> </tr> </tbody> </table> Bits 7:6 00: no parity, 1 stop bit 01: no parity, 2 stop bits 02: even parity, 1 stop bit 03: odd parity, 1 stop bit	Code	0x03	0x04	0x05	0x06	Baud	1200	2400	4800	9600	Code	0x07	0x08	0x09	0x0A	Baud	19200	38400	57600	115200	Refer to description	R/W	6
Code	0x03	0x04	0x05	0x06																				
Baud	1200	2400	4800	9600																				
Code	0x07	0x08	0x09	0x0A																				
Baud	19200	38400	57600	115200																				
40487	Type code 0x00: ±15 mV 0x01: ±50 mV 0x02: ±100 mV 0x03: ±500 mV 0x04: ±1 V 0x05: ±2.5 V 0x06: ±20 mA 0x0E: type J thermocouple 0x0F: type K thermocouple 0x10: type T thermocouple 0x11: type E thermocouple 0x12: type R thermocouple 0x13: type S thermocouple	Refer to description	R/W	5																				

	0x14: type B thermocouple 0x15: type N thermocouple 0x16: type C thermocouple 0x17: type L thermocouple 0x18: type M thermocouple 0x19: type L thermocouple			
40488	Modbus response delay time in ms, valid range: 0 ~ 30	0 to 30	R/W	0
40489	Host watchdog timeout value, 0 ~ 255, in 0.1s	0 to 255	R/W	255
40490	Enable/disable analog input channel, bit 0 for channel 0, bit 1 for channel 1, etc. 0 to disable and 1 to enable.	0 to 255	R/W	255
40491	Module CJC offset in 0.01°C	-4096 to 4096	R/W	0
40492	Host watchdog timeout count, write 0 to clear	0 to 65535	R/W	-
00257	Protocol, 0: DCON, 1: Modbus RTU	0: DCON 1: Modbus RTU	R/W	1
00259	Filter setting, 0: 60Hz rejection, 1: 50Hz rejection	0: 60Hz rejection 1: 50Hz rejection	R/W	0
00260	Modbus host watchdog mode 0: same as I-7000 (old mode) 1: can use AO and DO command to clear host watchdog timeout status (new mode)	0: old mode 1: new mode	R/W	0
00261	1: enable, 0: disable host watchdog	0: disable 1; enable	R/W	0
00268	1: enable, 0: disable CJC	0: disable 1; enable	R/W	1
00269	Modbus data format, 0: hex, 1: engineering	0: hex 1: engineering	R/W	0
00270	Host watch dog timeout status, write 1 to clear host watch dog timeout status	0: normal 1: host watchdog timeout	R/W	-
00273	Reset status, 1: first read after powered on, 0: not the first read after powered on	0: not reset 1: reset	R	-

M-7018Z

Address	Description	Data Format	Attribute	Factory Default																				
30001 ~ 30010 40001 ~ 40010	Analog input value of channel 0 to 9	-32768 to 32767 (0x8000 to 0x7FFF)	R	-																				
30129 40129	CJC temperature in 0.01°C	-5000 to 10000	R	-																				
40257 ~ 40266	Type code of channel 0 to 9 0x00: ±15 mV 0x01: ±50 mV 0x02: ±100 mV 0x03: ±500 mV 0x04: ±1 V 0x05: ±2.5 V 0x06: ±20 mA 0x0E: type J thermocouple 0x0F: type K thermocouple 0x10: type T thermocouple 0x11: type E thermocouple 0x12: type R thermocouple 0x13: type S thermocouple 0x14: type B thermocouple 0x15: type N thermocouple 0x16: type C thermocouple 0x17: type L thermocouple 0x18: type M thermocouple 0x19: type L thermocouple	Refer to description	R/W	5																				
40353 ~ 40362	CJC offset of channel 0 to 9 in 0.1°C. 1 for 0.1, 127 for 12.7, 255 for -0.1, 128 for -12.8	0 to 255	R/W	0																				
40481	Firmware version (low word)	0x0000	R	0x0000																				
40482	Firmware version (high word)	0xab0c for ab.c	R	-																				
40483	Module name (low word)	0x182A	R	0x182A																				
40484	Module name (high word)	0x0070	R	0x0070																				
40485	Module address, valid range: 1 ~ 247	1 to 247	R/W	1																				
40486	Bits 5:0 Baud rate, 0x03 ~ 0x0A <table border="1" style="margin-left: 20px;"> <tr> <td>Code</td> <td>0x03</td> <td>0x04</td> <td>0x05</td> <td>0x06</td> </tr> <tr> <td>Baud</td> <td>1200</td> <td>2400</td> <td>4800</td> <td>9600</td> </tr> <tr> <td>Code</td> <td>0x07</td> <td>0x08</td> <td>0x09</td> <td>0x0A</td> </tr> <tr> <td>Baud</td> <td>19200</td> <td>38400</td> <td>57600</td> <td>115200</td> </tr> </table> Bits 7:6 00: no parity, 1 stop bit	Code	0x03	0x04	0x05	0x06	Baud	1200	2400	4800	9600	Code	0x07	0x08	0x09	0x0A	Baud	19200	38400	57600	115200	Refer to description	R/W	6
Code	0x03	0x04	0x05	0x06																				
Baud	1200	2400	4800	9600																				
Code	0x07	0x08	0x09	0x0A																				
Baud	19200	38400	57600	115200																				

	01: no parity, 2 stop bits 02: even parity, 1 stop bit 03: odd parity, 1 stop bit			
40488	Modbus response delay time in ms, valid range: 0 ~ 30	0 to 30	R/W	0
40489	Host watchdog timeout value, 0 ~ 255, in 0.1s	0 to 255	R/W	255
40490	Enable/disable analog input channel, bit 0 for channel 0, bit 1 for channel 1, etc. 0 to disable and 1 to enable.	0 to 1023	R/W	1023
40491	Module CJC offset in 0.01°C	-4096 to 4096	R/W	0
40492	Host watchdog timeout count, write 0 to clear	0 to 65535	R/W	-
00257	Protocol, 0: DCON, 1: Modbus RTU	0: DCON 1: Modbus RtU	R/W	1
00259	Filter setting, 0: 60Hz rejection, 1: 50Hz rejection	0: 60Hz rejection 1: 50Hz rejection	R/W	0
00260	Modbus host watchdog mode 0: same as I-7000 (old mode) 1: can use AO and DO command to clear host watchdog timeout status (new mode)	0: old mode 1: new mode	R/W	0
00261	1: enable, 0: disable host watchdog	0: disable 1: enable	R/W	0
00268	1: enable, 0: disable CJC	0: disable 1: enable	R/W	1
00269	Modbus data format, 0: hex, 1: engineering	0: hex 1: engineering	R/W	0
00270	Host watch dog timeout status, write 1 to clear host watch dog timeout status	0: normal 1: host watchdog timeout	R/W	-
00273	Reset status, 1: first read after powered on, 0: not the first read after powered on	0: not reset 1: reset	R	-
00276	Open thermocouple detection, 1: enable, 0: disable (for firmware version B404 and later)	0: disable 1: enable	R/W	1

M-7018-16

Address	Description	Data Format	Attribute	Factory Default																				
30001 ~ 30016 40001 ~ 40016	Analog input value of channel 0 to 15	-32768 to 32767 (0x8000 to 0x7FFF)	R	-																				
30033 ~ 30048 40033 ~ 40048	Temperature reading of channel 0 to 15 in 1°C	-32768 to 32767 (0x8000 to 0x7FFF)	R	-																				
30129 40129	CJC temperature in 0.01°C	-5000 to 10000	R	-																				
40353 ~ 40368	CJC offset of channel 0 to 15 in 0.1°C. 1 for 0.1, 127 for 12.7, 255 for -0.1, 128 for -12.8	0 to 255	R/W	0																				
40481	Firmware version (low word)	0x0000	R	0x0000																				
40482	Firmware version (high word)	0xab0c for ab.c	R	-																				
40483	Module name (low word)	0x1810	R	0x1810																				
40484	Module name (high word)	0x0070	R	0x0070																				
40485	Module address, valid range: 1 ~ 247	1 to 247	R/W	1																				
40486	Bits 5:0 Baud rate, 0x03 ~ 0x0A <table border="1" data-bbox="380 1115 992 1276"> <thead> <tr> <th>Code</th> <th>0x03</th> <th>0x04</th> <th>0x05</th> <th>0x06</th> </tr> </thead> <tbody> <tr> <td>Baud</td> <td>1200</td> <td>2400</td> <td>4800</td> <td>9600</td> </tr> <tr> <th>Code</th> <th>0x07</th> <th>0x08</th> <th>0x09</th> <th>0x0A</th> </tr> <tr> <td>Baud</td> <td>19200</td> <td>38400</td> <td>57600</td> <td>115200</td> </tr> </tbody> </table> Bits 7:6 00: no parity, 1 stop bit 01: no parity, 2 stop bits 10: even parity, 1 stop bit 11: odd parity, 1 stop bit	Code	0x03	0x04	0x05	0x06	Baud	1200	2400	4800	9600	Code	0x07	0x08	0x09	0x0A	Baud	19200	38400	57600	115200	Refer to description	R/W	6
Code	0x03	0x04	0x05	0x06																				
Baud	1200	2400	4800	9600																				
Code	0x07	0x08	0x09	0x0A																				
Baud	19200	38400	57600	115200																				
40487	Type code 0x00: ±15 mV 0x01: ±50 mV 0x02: ±100 mV 0x03: ±500 mV 0x04: ±1 V 0x05: ±2.5 V 0x06: ±20 mA 0x0E: type J thermocouple 0x0F: type K thermocouple 0x10: type T thermocouple 0x11: type E thermocouple 0x12: type R thermocouple	Refer to description	R/W	5																				

	0x13: type S thermocouple 0x14: type B thermocouple 0x15: type N thermocouple 0x16: type C thermocouple 0x17: type L thermocouple 0x18: type M thermocouple 0x19: type L thermocouple			
40488	Modbus response delay time in ms, valid range: 0 ~ 30	0 to 30	R/W	0
40489	Host watchdog timeout value, 0 ~ 255, in 0.1s	0 to 255	R/W	255
40490	Enable/disable analog input channel, bit 0 for channel 0, bit 1 for channel 1, etc. 0 to disable and 1 to enable.	0 to 65535	R/W	65535
40491	Module CJC offset in 0.01°C	-4096 to 4096	R/W	0
40492	Host watchdog timeout count, write 0 to clear	0 to 65535	R/W	-
00257	Protocol, 0: DCON, 1: Modbus RTU	0: DCON 1: Modbus RTU	R/W	1
00259	Filter setting, 0: 60Hz rejection, 1: 50Hz rejection	0: 60Hz rejection 1: 50Hz rejection	R/W	0
00260	Modbus host watchdog mode 0: same as I-7000 (old mode) 1: can use AO and DO command to clear host watchdog timeout status (new mode)	0: old mode 1: new mode	R/W	0
00261	1: enable, 0: disable host watchdog	0: disable 1: enable	R/W	0
00268	1: enable, 0: disable CJC	0: disable 1: enable	R/W	1
00269	Modbus data format, 0: hex, 1: engineering	0: hex 1: engineering	R/W	0
00270	Host watch dog timeout status, write 1 to clear host watch dog timeout status	0: normal 1: host watchdog timeout	R/W	-
00273	Reset status, 1: first read after powered on, 0: not the first read after powered on	0: not reset 1; reset	R	-

M-7019R

(firmware version B300 and later)

Address	Description	Data Format	Attribute	Factory Default
10129 ~ 10136 00129 ~ 00136	Over/under range status of channel 0 to 7	0: normal 1: over/under	R	-
30001 ~ 30008 40001 ~ 40008	Analog input value of channel 0 to 7	-32768 to 32767 (0x8000 to 0x7FFF)	R	-
30129 40129	CJC temperature in 0.01°C	-5000 to 10000	R	-
40257 ~ 40264	Type code of channel 0 to 7 0x00: ±15 mV 0x01: ±50 mV 0x02: ±100 mV 0x03: ±500 mV 0x04: ±1 V 0x05: ±2.5 V 0x06: ±20 mA 0x07: 4 ~ 20 mA 0x08: ±10 V 0x09: ±5 V 0x0A: ±1 V 0x0B: ±500 mV 0x0C: ±150 mV 0x0D: ±20 mA 0x0E: type J thermocouple 0x0F: type K thermocouple 0x10: type T thermocouple 0x11: type E thermocouple 0x12: type R thermocouple 0x13: type S thermocouple 0x14: type B thermocouple 0x15: type N thermocouple 0x16: type C thermocouple 0x17: type L thermocouple 0x18: type M thermocouple 0x19: type L thermocouple 0x1A: 0 ~ 20 mA	Refer to description	R/W	8
40289 ~ 40296	Temperature offset of channel 0 to 7 in 0.1°C, valid range: -128 ~ 127	-128 to 127	R/W	0
40353 ~ 40360	CJC offset of channel 0 to 7 in 0.01°C, valid range: -4096 ~ 4096	-4096 to 4096	R/W	0

40481	Firmware version (low word)	0x0000	R	0x0000																				
40482	Firmware version (high word)	0xab0c for ab.c	R	-																				
40483	Module name (low word)	0x1922	R	0x1922																				
40484	Module name (high word)	0x0070	R	0x0070																				
40485	Module address, valid range: 1 ~ 247	1 to 247	R/W	1																				
40486	Bits 5:0 Baud rate, 0x03 ~ 0x0A <table border="1" data-bbox="360 499 992 659"> <tr> <td>Code</td> <td>0x03</td> <td>0x04</td> <td>0x05</td> <td>0x06</td> </tr> <tr> <td>Baud</td> <td>1200</td> <td>2400</td> <td>4800</td> <td>9600</td> </tr> <tr> <td>Code</td> <td>0x07</td> <td>0x08</td> <td>0x09</td> <td>0x0A</td> </tr> <tr> <td>Baud</td> <td>19200</td> <td>38400</td> <td>57600</td> <td>115200</td> </tr> </table> Bits 7:6 00: no parity, 1 stop bit 01: no parity, 2 stop bits 02: even parity, 1 stop bit 03: odd parity, 1 stop bit	Code	0x03	0x04	0x05	0x06	Baud	1200	2400	4800	9600	Code	0x07	0x08	0x09	0x0A	Baud	19200	38400	57600	115200	Refer to description	R/W	6
Code	0x03	0x04	0x05	0x06																				
Baud	1200	2400	4800	9600																				
Code	0x07	0x08	0x09	0x0A																				
Baud	19200	38400	57600	115200																				
40488	Modbus response delay time in ms, valid range: 0 ~ 30	0 to 30	R/W	0																				
40489	Host watchdog timeout value, 0 ~ 255, in 0.1s	0 to 255	R/W	255																				
40490	Enable/disable analog input channel, bit 0 for channel 0, bit 1 for channel 1, etc. 0 to disable and 1 to enable.	0 to 255	R/W	255																				
40491	Module CJC offset in 0.01°C	-4096 to 4096	R/W	0																				
40492	Host watchdog timeout count, write 0 to clear	0 to 65535	R/W	-																				
40493	CJC update setting, 0 ~ 2	0: stop 1: start 2: once	R/W	1																				
00257	Protocol, 0: DCON, 1: Modbus RTU	0: DCON 1: Modbus RTU	R/W	1																				
00259	Filter setting, 0: 60Hz rejection, 1: 50Hz rejection	0: 60Hz rejection 1: 50Hz rejection	R/W	0																				
00260	Modbus host watchdog mode 0: same as I-7000 (old mode) 1: can use AO and DO command to clear host watchdog timeout status (new mode)	0: old mode 1: new mode	R/W	0																				
00261	1: enable, 0: disable host watchdog	0: disable 1: enable	R/W	0																				
00268	1: enable, 0: disable CJC	0: disable 1: enable	R/W	1																				
00269	Modbus data format, 0: hex, 1: engineering	0: hex 1: engineering	R/W	1																				

00270	Host watch dog timeout status, write 1 to clear host watch dog timeout status	0: normal 1; host watchdog timeout	R/W	-
00273	Reset status, 1: first read after powered on, 0: not the first read after powered on	0: not reset 1: reset	R	-
00274	Sampling rate, 1: 8Hz, 0: 10Hz	0: 10Hz 1: 8Hz	R/W	0
00276	Open thermocouple detection (for firmware version B307 and later)	0: disable 1: enable	R/W	1

Notes:

1. The max number of analog output registers written in a command is 11.
2. The command of loading factory calibration parameters takes about 3 seconds.
The next command should be sent after 3 seconds.

M-7019Z

Address	Description	Data Format	Attribute	Factory Default
10129 ~ 10138 00129 ~ 00138	Over/under range status of channel 0 to 9	0: normal 1: over/under	R	-
30001 ~ 30010 40001 ~ 40010	Analog input value of channel 0 to 9	-32768 to 32767 (0x8000 to 0x7FFF)	R	-
30129 40129	CJC temperature in 0.01°C	-5000 to 10000	R	-
40257 ~ 40266	Type code of channel 0 to 9 0x00: ±15 mV 0x01: ±50 mV 0x02: ±100 mV 0x03: ±500 mV 0x04: ±1 V 0x05: ±2.5 V 0x06: ±20 mA 0x07: 4 ~ 20 mA 0x08: ±10 V 0x09: ±5 V 0x0A: ±1 V 0x0B: ±500 mV 0x0C: ±150 mV 0x0D: ±20 mA 0x0E: type J thermocouple 0x0F: type K thermocouple 0x10: type T thermocouple 0x11: type E thermocouple 0x12: type R thermocouple 0x13: type S thermocouple 0x14: type B thermocouple 0x15: type N thermocouple 0x16: type C thermocouple 0x17: type L thermocouple 0x18: type M thermocouple 0x19: type L thermocouple 0x1A: 0 ~ 20 mA	Refer to description	R/W	8
40289 ~ 40298	Temperature offset of channel 0 to 9 in 0.1°C, valid range: -128 ~ 127	-128 to 127	R/W	0
40353 ~ 40362	CJC offset of channel 0 to 9 in 0.01°C, valid range: -4096 ~ 4096	-4096 to 4096	R/W	0
40481	Firmware version (low word)	0x0000	R	0x0000

40482	Firmware version (high word)	0xab0c for ab.c	R	-					
40483	Module name (low word)	0x192A	R	0x192A					
40484	Module name (high word)	0x0070	R	0x0070					
40485	Module address, valid range: 1 ~ 247	1 to 247	R/W	1					
40486	Bits 5:0 Baud rate, 0x03 ~ 0x0A	Refer to description	R/W	6					
	Code				0x03	0x04	0x05	0x06	
	Baud				1200	2400	4800	9600	
	Code				0x07	0x08	0x09	0x0A	
	Baud	19200	38400	57600	115200				
	Bits 7:6 00: no parity, 1 stop bit 01: no parity, 2 stop bits 02: even parity, 1 stop bit 03: odd parity, 1 stop bit								
40488	Modbus response delay time in ms, valid range: 0 ~ 30	0 to 30	R/W	0					
40489	Host watchdog timeout value, 0 ~ 255, in 0.1s	0 to 255	R/W	255					
40490	Enable/disable analog input channel, bit 0 for channel 0, bit 1 for channel 1, etc. 0 to disable and 1 to enable.	0 to 1023	R/W	1023					
40491	Module CJC offset in 0.01°C	-4096 to 4096	R/W	0					
40492	Host watchdog timeout count, write 0 to clear	0 to 65535	R/W	-					
40493	CJC update setting, 0 ~ 2	0: stop 1: start 2: once	R/W	1					
00257	Protocol, 0: DCON, 1: Modbus RTU	0: DCON 1: Modbus RTU	R/W	1					
00259	Filter setting, 0: 60Hz rejection, 1: 50Hz rejection	0: 60Hz rejection 1: 50Hz rejection	R/W	0					
00260	Modbus host watchdog mode 0: same as I-7000 (old mode) 1: can use AO and DO command to clear host watchdog timeout status (new mode)	0: old mode 1: new mode	R/W	0					
00261	1: enable, 0: disable host watchdog	0: disable 1: enable	R/W	0					
00268	1: enable, 0: disable CJC	0: disable 1: enable	R/W	1					
00269	Modbus data format, 0: hex, 1: engineering	0: hex 1: engineering	R/W	1					

00270	Host watch dog timeout status, write 1 to clear host watch dog timeout status	0: normal 1: host watchdog timeout	R/W	
00272	Write 1 to reload factory calibration parameters	1: reload	W	-
00273	Reset status, 1: first read after powered on, 0: not the first read after powered on	0: not reset 1: reset	R	-
00276	Open thermocouple detection, 1: enable, 0: disable	0: disable 1: enable	R/W	1

Notes:

1. The max number of analog output registers written in a command is 11.
2. The command of loading factory calibration parameters takes about 3 seconds.
The next command should be sent after 3 seconds.

M-7022

(firmware version B102 and later)

Address	Description	Data Format	Attribute	Factory Default
40001 ~ 40002	Analog output value	Refer to M-7022 Data Format table below	R/W	-
40065 ~ 40066	Analog output read back	Refer to M-7022 Data Format table below	R	-
40097 ~ 40098	Safe output value	Refer to M-7022 Data Format table below	R/W	0
40193 ~ 40194	Power on output value	Refer to M-7022 Data Format table below	R/W	0
40257 ~ 40258	Type code	0: 0 ~ 20 mA 1: 4 ~ 20 mA 2: 0 ~ 10 V 4: 0 ~ 5 V	R/W	2
40289 ~ 40290	Slew rate 0x0: Immediate 0x1: 0.0625V/s or 0.125mA/s 0x2: 0.125V/s or 0.25mA/s 0x3: 0.25V/s or 0.5mA/s 0x4: 0.5V/s or 1.0mA/s 0x5: 1.0V/s or 2.0mA/s 0x6: 2.0V/s or 4.0mA/s 0x7: 4.0V/s or 8.0mA/s 0x8: 8.0V/s or 16.0mA/s 0x9: 16.0V/s or 32.0mA/s 0xA: 32.0V/s or 64.0mA/s 0xB: 64.0V/s or 128.0mA/s 0xC: 128.0V/s or 256.0mA/s 0xD: 256.0V/s or 512.0mA/s 0xE: 512.0V/s or 1024.0mA/s	Refer to description	R/W	0
40481	Firmware version (low word)	0x0000	R	0x0000
40482	Firmware version (high word)	0xab0c for ab.c	R	-
40483	Module name (low word)	0x2200	R	0x2200
40484	Module name (high word)	0x0070	R	0x0070
40485	Module address	1 to 247	R/W	1

40486	Baud rate	Bits 5:0, baud rate 03: 1200 04: 2400 05: 4800 06: 9600 07: 19200 08: 38400 09: 57600 0A: 115200 Bits 7:6, parity 00: N81 01: N82 02: E81 03: O81	R/W	6
40488	Modbus response delay time in ms	0 to 30	R/W	0
40489	Host watchdog timeout in 0.1s	0 to 255	R/W	255
40492	Host watchdog timeout count, write 0 to clear	0 to 65535	R/W	-
00257	Protocol, 0:DCON, 1:Modbus	0: DCON 1: Modbus	R/W	1
00258	Modbus Protocol, 0:RTU. 1:ASCII	0: Modbus RTU 1: Modbus ASCII	R/W	0
00260	Modbus host watchdog mode 0: same as I-7000 (old mode) 1: can use AO and DO command to clear host watchdog timeout (new mode)	0: old mode 1: new mode	R/W	0
00261	1: enable, 0:disable host watchdog	0: disable 1: enable	R/W	0
00269	Modbus data format, 0: hex, 1: engineering	0: hex 1: engineering	R/W	1
00270	Host watch dog timeout status, write 1 to clear host watch dog timeout status	0: normal 1: host watchdog timeout	R/W	-
00273	Reset status, 1: first read after powered on, 0: not the first read after powered on	0: not reset 1: reset	R	-

M-7022 Data Format

Type Code	Output Range	Data Format	Max	Min
0	0 ~ 20 mA	Engineering	20000	0
		Hexadecimal	0FFFh	0000h
1	4 ~ 20 mA	Engineering	20000	4000
		Hexadecimal	0FFFh	0000h
2	0 ~ 10 V	Engineering	10000	0
		Hexadecimal	0FFFh	0000h
4	0 ~ 5 V	Engineering	5000	0
		Hexadecimal	0FFFh	0000h

Note:

Engineering data format and type code 4 are supported by firmware version B102 and later.

M-7024

(firmware version A201 and later)

Address	Description	Data Format	Attribute	Factory Default
40001 ~ 40004	Analog output value	Refer to M-7024 Data Format table below	R/W	-
40065 ~ 40068	Analog output read back	Refer to M-7024 Data Format table below	R	-
40097 ~ 40100	Safe output value	Refer to M-7024 Data Format table below	R/W	0
40193 ~ 40196	Power on output value	Refer to M-7024 Data Format table below	R/W	0
40481	Firmware version (low word)	0x0000	R	0x0000
40482	Firmware version (high word)	0xab0c for ab.c	R	-
40483	Module name (low word)	0x2400	R	0x2400
40484	Module name (high word)	0x0070	R	0x0070
40485	Module address	1 to 247	R/W	1
40486	Baud rate	Bits 5:0, baud rate 03: 1200 04: 2400 05: 4800 06: 9600 07: 19200 08: 38400 09: 57600 0A: 115200 Bits 7:6, parity 00: N81 01: N82 02: E81 03: O81	R/W	6
40487	Type code	0x30: 0 ~ 20 mA 0x31: 4 ~ 20 mA 0x32: 0 ~ 10 V 0x33: -10 ~ +10 V 0x34: 0 ~ 5 V 0x35: -5 ~ +5 V	R/W	0x32
40488	Modbus response delay time in ms	0 to 30	R/W	0

40489	Host watchdog timeout in 0.1s	0 to 255	R/W	255
40492	Host watchdog timeout count, write 0 to clear	0 to 65535	R/W	-
40494	Slew rate	0x0: Immediate 0x1: 0.0625V/s or 0.125mA/s 0x2: 0.125V/s or 0.25mA/s 0x3: 0.25V/s or 0.5mA/s 0x4: 0.5V/s or 1.0mA/s 0x5: 1.0V/s or 2.0mA/s 0x6: 2.0V/s or 4.0mA/s 0x7: 4.0V/s or 8.0mA/s 0x8: 8.0V/s or 16.0mA/s 0x9: 16.0V/s or 32.0mA/s 0xA: 32.0V/s or 64.0mA/s 0xB: 64.0V/s or 128.0mA/s 0xC: 128.0V/s or 256.0mA/s 0xD: 256.0V/s or 512.0mA/s 0xE: 512.0V/s or 1024.0mA/s 0xF: 1024.0V/s or 2048.0mA/s	R/W	0
00257	Protocol, 0:DCON, 1:Modbus		R/W	
00260	Modbus host watchdog mode 0: same as I-7000 1: can use AO and DO command to clear host watchdog timeout		R/W	
00261	1: enable, 0:disable host watchdog		R/W	
00269	Modbus data format, 0: hex, 1: engineering		R/W	
00270	Host watch dog timeout status, write 1 to clear host watch dog timeout status		R/W	
00273	Reset status, 1: first read after powered on, 0: not the first read after powered on		R	

M-7024 Data Format

Type Code	Output Range	Data Format	+F.S.	-F.S.
30	0 to 20 mA	Engineering	20000	0
		Hexadecimal	3FFF	0000
31	4 to 20 mA	Engineering	20000	04000
		Hexadecimal	3FFF	0000
32	0 to +10 V	Engineering	10000	0
		Hexadecimal	3FFF	0000
33	-10 to +10 V	Engineering	+10000	-10000
		Hexadecimal	3FFF	C000
34	0 to +5 V	Engineering	+5000	0
		Hexadecimal	3FFF	0000
35	-5 to +5 V	Engineering	+5000	-5000
		Hexadecimal	3FFF	C000

M-7024R

Address	Description	Data Format	Attribute	Factory Default
40001 ~ 40004	Analog output value	Refer to M-7024R Data Format table below	R/W	-
40065 ~ 40068	Analog output read back	Refer to M-7024R Data Format table below	R	-
40097 ~ 40100	Safe output value	Refer to M-7024R Data Format table below	R/W	0
40129 ~ 40133	Counter value of digital input	0 to 65535	R	-
40193 ~ 40196	Power on output value	Refer to M-7024R Data Format table below	R/W	0
00033 ~ 00037	Digital input value	0: off 1: on	R	-
00065 ~ 00069	High latched value of DI	0: normal 1: latched	R	-
00097 ~ 00101	Low latched value of DI	0: normal 1: latched	R	-
40481	Firmware version (low word)	0x0000	R	0x0000
40482	Firmware version (high word)	0xab0c for ab.c	R	-
40483	Module name (low word)	0x2422	R	0x2422
40484	Module name (high word)	0x0070	R	0x0070
40485	Module address	1 to 247	R/W	1
40486	Baud rate	Bits 5:0, baud rate 03: 1200 04: 2400 05: 4800 06: 9600 07: 19200 08: 38400 09: 57600 0A: 115200 Bits 7:6, parity 00: N81 01: N82 02: E81 03: O81	R/W	6

40487	Type code	0x30: 0 ~ 20 mA 0x31: 4 ~ 20 mA 0x32: 0 ~ 10 V 0x33: -10 ~ +10 V 0x34: 0 ~ 5 V 0x35: -5 ~ +5 V	R/W	0x32
40488	Modbus response delay time in ms	0 to 30	R/W	0
40489	Host watchdog timeout in 0.1s	0 to 255	R/W	255
40492	Host watchdog timeout count, write 0 to clear	0 to 65535	R/W	-
40494	Slew rate	0x0: Immediate 0x1: 0.0625V/s or 0.125mA/s 0x2: 0.125V/s or 0.25mA/s 0x3: 0.25V/s or 0.5mA/s 0x4: 0.5V/s or 1.0mA/s 0x5: 1.0V/s or 2.0mA/s 0x6: 2.0V/s or 4.0mA/s 0x7: 4.0V/s or 8.0mA/s 0x8: 8.0V/s or 16.0mA/s 0x9: 16.0V/s or 32.0mA/s 0xA: 32.0V/s or 64.0mA/s 0xB: 64.0V/s or 128.0mA/s 0xC: 128.0V/s or 256.0mA/s 0xD: 256.0V/s or 512.0mA/s 0xE: 512.0V/s or 1024.0mA/s 0xF: 1024.0V/s or 2048.0mA/s	R/W	0
00257	Protocol, 0:DCON, 1:Modbus	0: DCON 1: Modbus RTU	R/W	1
00260	Modbus host watchdog mode 0: same as I-7000 (old mode) 1: can use AO and DO command to clear host watchdog timeout (new mode)	0: old mode 1: new mode	R/W	0

00261	1: enable, 0:disable host watchdog	0: disable 1: enable	R/W	0
00264	Write 1 to clear latched DI	1: clear	W	-
00269	Modbus data format, 0: hex, 1: engineering	0: hex 1: engineering	R/W	1
00270	Host watch dog timeout status, write 1 to clear host watch dog timeout status	0: normal 1: host watchdog timeout	R/W	-
00273	Reset status, 1: first read after powered on, 0: not the first read after powered on	0: not reset 1: reset	R	-
00513 00517	~ Write 1 to clear DI counter value	1: clear	W	-

M-7024R Data Format

Type Code	Output Range	Data Format	+F.S.	-F.S.
30	0 to 20 mA	Engineering	20000	0
		Hexadecimal	3FFF	0000
31	4 to 20 mA	Engineering	20000	04000
		Hexadecimal	3FFF	0000
32	0 to +10 V	Engineering	10000	0
		Hexadecimal	3FFF	0000
33	-10 to +10 V	Engineering	+10000	-10000
		Hexadecimal	3FFF	C000
34	0 to +5 V	Engineering	+5000	0
		Hexadecimal	3FFF	0000
35	-5 to +5 V	Engineering	+5000	-5000
		Hexadecimal	3FFF	C000

M-7024U

Address	Description	Data Format	Attribute	Factory Default
30065 ~ 30068 40065 ~ 40068	Analog output read back of channel 0 to 3	Refer to M-7024U Data Format table below	R	-
30129 ~ 30132 40129 ~ 40132	Counter value of digital input channel 0 to 3	0 to 65535	R	-
40001 ~ 40004	Analog output value of channel 0 to 3	Refer to M-7024U Data Format table below	R/W	-
40097 ~ 40100	Safe analog output value of channel 0 to 3	Refer to M-7024U Data Format table below	R/W	-
40193 ~ 40196	Power on analog output value of channel 0 to 3	Refer to M-7024U Data Format table below	R/W	-
40257 ~ 40260	Analog output type code of channel 0 to 3	0: 0 ~ 20 mA 1: 4 ~ 20 mA 2: 0 ~ 10 V 3: -10 ~ +10 V 4: 0 ~ 5 V 5: -5 ~ +5 V	R/W	2
40289 ~ 40292	Analog output slew rate of channel 0 to 3	0x0: Immediate 0x1: 0.0625V/s or 0.125mA/s 0x2: 0.125V/s or 0.25mA/s 0x3: 0.25V/s or 0.5mA/s 0x4: 0.5V/s or 1.0mA/s 0x5: 1.0V/s or 2.0mA/s 0x6: 2.0V/s or 4.0mA/s 0x7: 4.0V/s or 8.0mA/s 0x8: 8.0V/s or 16.0mA/s 0x9: 16.0V/s or 32.0mA/s 0xA: 32.0V/s or 64.0mA/s	R/W	0

		0xB: 64.0V/s or 128.0mA/s 0xC: 128.0V/s or 256.0mA/s 0xD: 256.0V/s or 512.0mA/s 0xE: 512.0V/s or 1024.0mA/s 0xF: 1024.0V/s or 2048.0mA/s																						
40481	Firmware version (low word)	0x0000	R	0x0000																				
40482	Firmware version (high word)	0xab0c for ab.c	R	-																				
40483	Module name (low word), 0x0070	0x2425	R	0x2425																				
40484	Module name (high word), 0x2425	0x0070	R	0x0070																				
40485	Module address, valid range: 1 ~ 247	1 to 247	R/W	1																				
40486	Bits 5:0 Baud rate, 0x03 ~ 0x0A <table border="1" style="margin-left: 20px;"> <tr> <td>Code</td> <td>0x03</td> <td>0x04</td> <td>0x05</td> <td>0x06</td> </tr> <tr> <td>Baud</td> <td>1200</td> <td>2400</td> <td>4800</td> <td>9600</td> </tr> <tr> <td>Code</td> <td>0x07</td> <td>0x08</td> <td>0x09</td> <td>0x0A</td> </tr> <tr> <td>Baud</td> <td>19200</td> <td>38400</td> <td>57600</td> <td>115200</td> </tr> </table> Bits 7:6 00: no parity, 1 stop bit 01: no parity, 2 stop bits 02: even parity, 1 stop bit 03: odd parity, 1 stop bit	Code	0x03	0x04	0x05	0x06	Baud	1200	2400	4800	9600	Code	0x07	0x08	0x09	0x0A	Baud	19200	38400	57600	115200	Refer to description	R/W	6
Code	0x03	0x04	0x05	0x06																				
Baud	1200	2400	4800	9600																				
Code	0x07	0x08	0x09	0x0A																				
Baud	19200	38400	57600	115200																				
40488	Modbus response delay time in ms	0 to 30	R/W	0																				
40489	Host watchdog timeout value, 0 ~ 255, in 0.1s	0 to 255	R/W	255																				
40492	Host watchdog timeout count, write 0 to clear	0 to 65535	R/W	-																				
00033 ~ 00046 10033 ~ 10046	Digital input value of channel 0 to 3	0: off 1: on	R	-																				
00065 ~ 00068 10065 ~ 10068	High latched value of DI	0: normal 1: latched	R	-																				
00073 ~ 00076 10073 ~ 10076	High latched value of DO	0: normal 1: latched	R	-																				
00097 ~ 00100	Low latched value of DI	0: normal 1: latched	R	-																				

10097 ~ 10100				
00105 ~ 00108 10105 ~ 10108	Low latched value of DO	0: normal 1: latched	R	-
00225 ~ 00228 10225 ~ 10228	Status of current output open wire or voltage output short circuit	0: normal 1: open/short	R	-
00001 ~ 00004	Digital output value of channel 0 to 3	0: off 1: on	R/W	-
00129 ~ 00132	Safe value of digital output channel 0 to 3	0: off 1: on	R/W	0
00161 ~ 00164	Power on value of digital output channel 0 to 3	0: off 1: on	R/W	0
00193 ~ 00196	Counter update trigger edge of digital input channel 0 to 3	0: falling edge 1: rising edge	R/W	0
00257	Protocol, 0: DCON, 1: Modbus	0: DCON 1: Modbus RTU	R/W	1
00260	Modbus host watchdog mode 0: same as I-7000 (old mode) 1: can use AO and DO command to clear host watchdog timeout status (new mode)	0: old mode 1: new mode	R/W	0
00261	1: enable, 0: disable host watchdog	0: disable 1: enable	R/W	0
00264	Write 1 to clear latched DIO states	1: clear	W	-
00265	DI active state	0: normal 1: inversed	R/W	0
00266	DO active state	0: normal 1: inversed	R/W	0
00269	Modbus data format, 0: hex, 1: engineering	0: hex 1: engineering	R/W	1
00270	Host watch dog timeout status, write 1 to clear host watch dog timeout status	0: normal 1: host watchdog timeout	R/W	-
00272	Write 1 to reload factory default calibration parameters	1: reload	W	-
00273	Reset status, 1: first read after powered on, 0: not the first read after powered on	0: not reset 1: reset	R	-
00513 ~ 00516	Write 1 to clear counter value of digital input channel 0 to 3	1: clear	W	-
00769 ~ 00772	Enable retained analog output for channel 0 to 3	0: disable 1: enable	R/W	0

M-7024U Data Format

Type Code	Range	Data Format	Minimum	Maximum
0	0 mA ~ +20 mA	Engineering	0	+20000
		Hexadecimal	0000h	FFFFh
1	+4 mA ~+20 mA	Engineering	+4000	+20000
		Hexadecimal	0000h	FFFFh
2	0V ~ +10 V	Engineering	0	+10000
		Hexadecimal	0000h	FFFFh
3	+/-10 V	Engineering	-10000	+10000
		Hexadecimal	8000h	7FFFh
4	0 V ~ +5 V	Engineering	0	+5000
		Hexadecimal	0000h	FFFFh
5	+/-5 V	Engineering	-5000	+5000
		Hexadecimal	8000h	7FFFh

M-7026

Address	Description	Data Format	Attribute	Factory Default
00001 ~ 00003	Reads the current status of the Digital Output or sets the Digital Output to either active or inactive	0: on 1: off	R/W	-
00129 ~ 00131	Reads/sets the Digital Output Safe Value	0: on 1: off	R/W	0
00161 ~ 00163	Reads/sets the Digital Output Power-on Value	0: on 1: off	R/W	0
00193 ~ 00195	Reads/sets the status of the Digital Input Edge	0: Falling Edge 1: Rising Edge	R/W	0
00257	Reads/sets the Communication Protocol	0: DCON 1: Modbus RTU	R/W	1
00259	Reads/sets the Filter Settings	0: 60Hz rejection 1: 50Hz rejection	R/W	0
00260	Reads/sets the Host Watchdog Mode 0: The same as for I-7000 series modules (old mode) 1: Analog Output and Digital Output commands can be used to clear the status of the Host Watchdog timeout (new mode)	0: old mode 1: new mode	R/W	0
00261	Enables or disables the Host Watchdog, or reads the status of the Host Watchdog	0: disable 1: enable	R/W	0
00264	Clears the latched Digital Input and Digital Output channels. Write 1 to clear	1: clear	W	-
00265	Sets the active Digital Input mode:	0: normal 1: inverse	W	0
00266	Sets the active Digital Output mode:	0: normal 1: inverse	W	0
00269	Reads/sets the Modbus Data Format	0: hex 1: engineering	R/W	1
00270	Reads the status of the Host Watchdog timeout. Write 1 to clear.	0: normal 1: host watchdog timeout	R/W	-
00271	Reads/sets the Analog Input Filter Format	0: normal 1: fast	R/W	0
00272	Reloads the factory calibration parameters.	1: reload	W	-
00273	Reads the Reset status 0: This is NOT the first time the module has been read since being powered on 1: This is the first time the module has been read since being powered on	0: not reset 1: reset	R	-
00280	Clears the high latch values for all Analog Input channels. Write 1 to clear.	1: clear	W	-
00281	Clears the low latch values for all Analog Input channels. Write 1 to clear.	1: clear	W	-

00284	Enables or disables calibration, or reads the status of the calibration function	0: disable 1: enable	R/W	-
00285	Sets the Analog Input zero calibration.	1: zero calibration	W	-
00286	Sets the Analog Input span calibration.	1: span calibration	W	-
00289 ~ 00294	Reads/clears the status of the low alarm for channels 0 to 5. Write 1 to clear.	0: normal 1: alarmed	R/W	-
00305 ~ 00310	Reads/clears the status of the high alarm for channels 0 to 5. Write 1 to clear.	0: normal 1: alarmed	R/W	-
00321 ~ 00326	Enables or disables the Analog Input Alarm, or reads the status of the Analog Input Alarm	0: disable 1: enable	R/W	0
00337 ~ 00342	Reads/sets the Analog Input Alarm mode	0: momentary 1: latched	R/W	0
00385 ~ 00390	Clears the high latched Analog Input for channels 0 to 5. Write 1 to clear.	1: clear	W	-
00417 ~ 00422	Clears the low latched Analog Input for channels 0 to 5. Write 1 to clear.	1: clear	W	-
00513 ~ 00515	Resets the Digital Input counter for channels 0 to 2. Write 1 to reset.	1: reset	W	-
10033 ~ 10035	Reads the status of the Digital Input for channels 0 to 2	0: on 1: off	R	-
10065 ~ 10067	Reads the status of the high latched Digital Input channels	0: normal 1: latched	R	-
10073 ~ 10075	Reads the status of the high latched Digital Output channels	0: normal 1: latched	R	-
10097~ 10099	Reads the status of the low latched Digital Input channels	0: normal 1: latched	R	-
10105 ~ 10107	Reads the status of the low latched Digital Output channels	0: normal 1: latched	R	-
10225 ~ 10230	Reads whether or not Analog Input channels 0 to 5 are under range	0: normal 1: under	R	-
10241 ~ 10242	Reads the status of the wire connection for Analog Output channels 0 to 1	0: normal 1: open	R	-
30001 ~ 30006	Reads the Analog Input value for channels 0 to 5	-32768 to 32767 (0x8000 to 0x7FFF)	R	-
30065 ~ 30066	Reads the current output value for Analog Output channels 0 to 1	-32768 to 32767 (0x8000 to 0x7FFF)	R	-
30129 ~ 30131	Reads the Digital Input counter for channels 0 to 2	0 to 65535	R	-
30513 ~ 30518	Reads the high latch value for Analog Input channels 0 to 5	-32768 to 32767 (0x8000 to 0x7FFF)	R	-
30545 ~ 30550	Reads the low latch value for Analog Input channels 0 to 5	-32768 to 32767 (0x8000 to 0x7FFF)	R	-
40033 ~ 40034	Reads/writes the Analog Output value for channels 0 to 1	-32768 to 32767 (0x8000 to 0x7FFF)	R/W	-
40097 ~ 40098	Reads/writes the safe value for Analog Output channels 0 to 1	-32768 to 32767 (0x8000 to 0x7FFF)	R/W	0

40193 ~ 40194	Reads/writes the power-on value for Analog Output channels 0 to 1	-32768 to 32767 (0x8000 to 0x7FFF)	R/W	0
40225 ~ 40230	Reads/writes the Analog Input high alarm value	-32768 to 32767 (0x8000 to 0x7FFF)	R/W	32767
40233 ~ 40238	Reads/writes the Analog Input low alarm value	-32768 to 32767 (0x8000 to 0x7FFF)	R/W	-32768
40257 ~ 40262	Reads/writes the Type Code for Analog Input channels 0 to 5	0x07: 4 ~ 20 mA 0x08: ±10 V 0x09: ±5 V 0x0A: ±1 V 0x0B: ±500 mV 0x0C: ±150 mV 0x0D: ±20 mA 0x1A: 0 ~ 20 mA	R/W	8
40289 ~ 40290	Reads/writes the Analog Output Slew Rate for channels 0 to 1	0x0: Immediate 0x1: 0.0625V/s or 0.125mA/s 0x2: 0.125V/s or 0.25mA/s 0x3: 0.25V/s or 0.5mA/s 0x4: 0.5V/s or 1.0mA/s 0x5: 1.0V/s or 2.0mA/s 0x6: 2.0V/s or 4.0mA/s 0x7: 4.0V/s or 8.0mA/s 0x8: 8.0V/s or 16.0mA/s 0x9: 16.0V/s or 32.0mA/s 0xA: 32.0V/s or 64.0mA/s 0xB: 64.0V/s or 128.0mA/s 0xC: 128.0V/s or 256.0mA/s 0xD: 256.0V/s or 512.0mA/s 0xE: 512.0V/s or 1024.0mA/s 0xF: 1024.0V/s or 2048.0mA/s	R/W	0
40417 ~ 40418	Reads/writes the Type Code for Analog Output channels 0 to 1	0: 0 ~ 20 mA 1: 4 ~ 20 mA 2: 0 ~ 10 V	R/W	2

		3: -10 ~ +10 V 4: 0 ~ 5 V 5: -5 ~ +5 V		
40481	Reads the Firmware Version (high word)	0x0000	R	0x0000
40482	Reads the Firmware Version (low word)	0xab0c for ab.c	R	-
40483	Reads the Name of the Module (high word)	0x2600	R	0x2600
40484	Reads the Name of the Module (low word)	0x0070	R	0x0070
40485	Reads the Module address. The valid range is 0x1 to 0xF7	1 to 247	R	1
40486	Reads/writes the Baud Rate Bits 5:0 Baud Rate Bits 7:6 Reserved	Bits 5:0, baud rate 03: 1200 04: 2400 05: 4800 06: 9600 07: 19200 08: 38400 09: 57600 0A: 115200 Bits 7:6, parity 00: N81 01: N82 02: E81 03: O81	R/W	6
40488	Reads/writes the Response Delay Time in ms. The valid range is 0 to 30ms.	0 to 30	R/W	0
40489	Reads/writes the Host Watchdog Timeout value in 0.1s increments. The valid range is 0 to 255.	0 to 255	R/W	255
40490	Enable/disable analog input channel, bit 0 for channel 0, bit 1 for channel 1, etc. 0 to disable and 1 to enable.	0 to 63	R/W	63
40492	Reads/clears the Host Watchdog Timeout count. Write 0 to clear.	0 to 65535	R/W	-

Note:

The command to load the factory calibration parameters (00272) takes about 3 seconds to be processed. Subsequent commands should not be sent before this time has elapsed.

M-7028

Address	Description	Data Format	Attribute	Factory Default
30065 ~ 30072 40065 ~ 40072	Analog output read back of channel 0 to 7	Refer to M-7028 Data Table below	R	-
40001 ~ 40008	Analog output value of channel 0 to 7	Refer to M-7028 Data Table below	R/W	-
40097 ~ 40104	Safe analog output value of channel 0 to 7	Refer to M-7028 Data Table below	R/W	0
40193 ~ 40200	Power on analog output value of channel 0 to 7	Refer to M-7028 Data Table below	R/W	0
40257 ~ 40264	Analog output type code of channel 0 to 7	0: 0 ~ 20 mA 1: 4 ~ 20 mA 2: 0 ~ 10 V 3: -10 ~ +10 V 4: 0 ~ 5 V 5: -5 ~ +5 V	R/W	2
40289 ~ 40296	Analog output slew rate of channel 0 to 7	0x0: Immediate 0x1: 0.0625V/s or 0.125mA/s 0x2: 0.125V/s or 0.25mA/s 0x3: 0.25V/s or 0.5mA/s 0x4: 0.5V/s or 1.0mA/s 0x5: 1.0V/s or 2.0mA/s 0x6: 2.0V/s or 4.0mA/s 0x7: 4.0V/s or 8.0mA/s 0x8: 8.0V/s or 16.0mA/s 0x9: 16.0V/s or 32.0mA/s 0xA: 32.0V/s or 64.0mA/s 0xB: 64.0V/s or 128.0mA/s 0xC: 128.0V/s or 256.0mA/s 0xD: 256.0V/s or 512.0mA/s 0xE: 512.0V/s or	R/W	0

		1024.0mA/s 0xF: 1024.0V/s or 2048.0mA/s						
40481	Firmware version (low word)	0x0000	R	0x0000				
40482	Firmware version (high word)	0xab0c for ab.c	R	-				
40483	Module name (low word), 0x2800	0x2800	R	0x2800				
40484	Module name (high word), 0x0070	0x0070	R	0x0070				
40485	Module address, valid range: 1 ~ 247	1 to 247	R/W	1				
40486	Bits 5:0 Baud rate, 0x03 ~ 0x0A	Refer to description	R/W	6				
	Code				0x03	0x04	0x05	0x06
	Baud				1200	2400	4800	9600
	Code				0x07	0x08	0x09	0x0A
	Baud	19200	38400	57600	115200			
	Bits 7:6 00: no parity, 1 stop bit 01: no parity, 2 stop bits 02: even parity, 1 stop bit 03: odd parity, 1 stop bit							
40488	Modbus response delay time in ms	0 to 30	R/W	0				
40489	Host watchdog timeout value, 0 ~ 255, in 0.1s	0 to 255	R/W	255				
40492	Host watchdog timeout count, write 0 to clear	0 to 65535	R/W	-				
00225 ~ 00232 10225 ~ 10232	Status of current output open wire	0: normal 1: open	R	-				
00257	Protocol, 0: DCON, 1: Modbus	0: DCON 1: Modbus RTU	R/W	1				
00260	Modbus host watchdog mode 0: same as I-7000 (old mode) 1: can use AO and DO command to clear host watchdog timeout status (new mode)	0: old mode 1: new mode	R/W	0				
00261	1: enable, 0: disable host watchdog	0: disable 1: enable	R/W	0				
00269	Modbus data format, 0: hex, 1: engineering	0: hex 1: engineering	R/W	1				
00270	Host watch dog timeout status, write 1 to clear host watch dog timeout status	0: normal 1: host watchdog timeout	R/W	-				
00272	Write 1 to reload factory default calibration parameters	1: reload	W	-				
00273	Reset status, 1: first read after powered on, 0: not the first read after powered on	0: not reset 1: reset	R	-				

M-7028 Data Format

Type Code	Range	Data Format	Minimum	Maximum
0	0 mA ~ +20 mA	Engineering	0	+20000
		Hexadecimal	0000h	FFFFh
1	+4 mA ~+20 mA	Engineering	+4000	+20000
		Hexadecimal	0000h	FFFFh
2	0V ~ +10 V	Engineering	0	+10000
		Hexadecimal	0000h	FFFFh
3	+/-10 V	Engineering	-10000	+10000
		Hexadecimal	8000h	7FFFh
4	0 V ~ +5 V	Engineering	0	+5000
		Hexadecimal	0000h	FFFFh
5	+/-5 V	Engineering	-5000	+5000
		Hexadecimal	8000h	7FFFh

M-7033

Address	Description	Data Format	Attribute	Factory Default
30001 40001	Analog input value of channel 0	0x8000 to 0x7FFF	R	-
30002 40002	Analog input value of channel 1	0x8000 to 0x7FFF	R	-
30003 40003	Analog input value of channel 2	0x8000 to 0x7FFF	R	-

M-7000 DIO

Address	Description	Data Format	Attribute	Factory Default																				
30001 ~ 30016	Counter value of digital input	0 to 65535	R	-																				
40001 ~ 40016	Counter value of digital input	0 to 65535	R	-																				
40481*1	Firmware version (low word)	0x0000 to 0xFFFF	R	-																				
40482*1	Firmware version (high word)	0x0000 to 0xFFFF	R	-																				
40483*1	Module name (low word)	0x0000 to 0xFFFF	R	-																				
40484*1	Module name (high word)	0x0000 to 0xFFFF	R	-																				
40485*1	Module address, valid range: 1 ~ 247	1 to 247	R/W	1																				
40486*1	Bits 5:0 Baud rate, 0x03 ~ 0x0A <table border="1" data-bbox="378 804 992 963"> <tbody> <tr> <td>Code</td> <td>0x03</td> <td>0x04</td> <td>0x05</td> <td>0x06</td> </tr> <tr> <td>Baud</td> <td>1200</td> <td>2400</td> <td>4800</td> <td>9600</td> </tr> <tr> <td>Code</td> <td>0x07</td> <td>0x08</td> <td>0x09</td> <td>0x0A</td> </tr> <tr> <td>Baud</td> <td>19200</td> <td>38400</td> <td>57600</td> <td>115200</td> </tr> </tbody> </table> Bits 7:6 00: no parity, 1 stop bit 01: no parity, 2 stop bits 02: even parity, 1 stop bit 03: odd parity, 1 stop bit	Code	0x03	0x04	0x05	0x06	Baud	1200	2400	4800	9600	Code	0x07	0x08	0x09	0x0A	Baud	19200	38400	57600	115200	Refer to description	R/W	6
Code	0x03	0x04	0x05	0x06																				
Baud	1200	2400	4800	9600																				
Code	0x07	0x08	0x09	0x0A																				
Baud	19200	38400	57600	115200																				
40488*1	Modbus response delay time in ms, valid range: 0 ~ 30	0 to 30	R/W	0																				
40489*1	Host watchdog timeout value, 0 ~ 255, in 0.1s	0 to 255	R/W	255																				
40492*1	Host watchdog timeout count, write 0 to clear	0 to 65535	R/W	-																				
10001 ~ 10016	Digital input value	0: off 1: on	R	-																				
00001 ~ 00016	Digital output value	0: off 1: on	R/W	-																				
00033 ~ 00048	Digital input value of channel 0 ~ 7	0: off 1: on	R	-																				
00065 ~ 00096	High latched values of DIO	0: normal 1: latched	R	-																				
00097 ~ 00128	Low latched values of DIO	0: normal 1: latched	R	-																				
00129 ~ 00144	Safe value of digital output channel	0: off 1: on	R/W	0																				
00161 ~ 00176	Power on value of digital output channel	0: off 1: on	R/W	0																				

00193*1 ~ 00208	Counter update trigger edge of digital input channel	0: falling edge 1: rising edge	R/W	0
00257*2	Write 1 to clear latch values	1: clear	W	-
00257*1	Protocol, 0: DCON, 1: Modbus RTU	0: DCON 1: Modbus	R/W	1
00258*1	0: Modbus RTU, 1: Modbus ASCII	0: Modbus RTU 1: Modbus ASCII	R/W	0
00260*1	Modbus host watchdog mode 0: same as I-7000 (old mode) 1: can use write DO command to clear host watchdog timeout status (new mode)	0: old mode 1: new mode	R/W	0
00261*1	1: enable, 0: disable host watchdog	0: disable 1: enable	R/W	0
00264*1	Write 1 to clear latched DIO	1: clear	W	-
00265*1	DI active state, 0: normal, 1: inverse	0: normal 1: inverse	R/W	0
00266*1	DO active state, 0: normal, 1:inverse	0: normal 1: inverse	R/W	0
00270*1	Host watch dog timeout status, write 1 to clear host watch dog timeout status	0: normal 1: host watchdog timeout	R/W	-
00273*1	Reset status, 1: first read after powered on, 0: not the first read after powered on	0: not reset 1: reset	R	-
00513 ~ 00528	Write 1 to clear counter value of digital input channel	1: clear	W	-

Note:

*1: only available with firmware version 200 and later

*2: only available with firmware version 199 and earlier

M-7080

Address	Description	Data Format	Attribute	Factory Default
40001	Counter/frequency value of channel 0 (low word)	0 to 65535	R	-
40002	Counter/frequency value of channel 0 (high word)	0 to 65535	R	-
40003	Counter/frequency value of channel 1 (low word)	0 to 65535	R	-
40004	Counter/frequency value of channel 1 (high word)	0 to 65535	R	-
40065	Max. value of counter 0 (low word)	0 to 65535	R/W	65535
40066	Max. value of counter 0 (high word)	0 to 65535	R/W	65535
40067	Max. value of counter 1 (low word)	0 to 65535	R/W	65535
40068	Max. value of counter 1 (high word)	0 to 65535	R/W	65535
40097	Preset value of counter 0 (low word)	0 to 65535	R/W	0
40098	Preset value of counter 0 (high word)	0 to 65535	R/W	0
40099	Preset value of counter 1 (low word)	0 to 65535	R/W	0
40100	Preset value of counter 1 (high word)	0 to 65535	R/W	0
40161	Low level width threshold in us	2 to 65535	R/W	2
40162	High level width threshold in us	2 to 65535	R/W	2
40163	Low voltage trigger value in 0.1V	0 to 50	R/W	8
40164	High voltage trigger value in 0.1V	0 to 50	R/W	24
00001	DO 0	0: off 1: on	R/W	-
00002	DO 1	0: off 1: on	R/W	-
00065	Overflow flag of counter 0	0: normal 1: overflow	R	-
00066	Overflow flag of counter 1	0: normal 1: overflow	R	-
00129	Input mode of channel 0, 0:non-isolated, 1:isolated	0:non-isolated 1:isolated	R/W	0
00130	Input mode of channel 1, 0:non-isolated, 1:isolated	0:non-isolated 1:isolated	R/W	0
00131	0: gate is low active, 1: gate is high active, when gate control is enabled	0: low active 1: high active	R/W	0
00132	Gate control, 0: enable, 1:disable	0: disable 1: enable	R/W	0
00133	Set counter 0 to preset value	1: preset	W	-

00134	Set counter 1 to preset value	1: preset	W	-
00135	Start(1)/Stop(0) counter 0	0: stop 1: start	R/W	1
00136	Start(1)/Stop(0) counter 1	0: stop 1: start	R/W	1
00139	Enable(1)/disable(0) digital filter	0: disable 1: enable	R/W	0
00142	Frequency gate time, 0:0.1second, 1: 1.0second	0: 0.1s 1: 1.0s	R/W	0
00143	LED configuration, 0:ch0, 1: ch1	0: ch0 1: ch1	R/W	0
00145*1	Counter mode of channel 0, 1: stop counting on overflow, 0: continuous	0: continuous 1: stop counting	R/W	-
00146*1	Counter mode of channel 1, 1: stop counting on overflow, 0: continuous	0: continuous 1: stop counting	R/W	-

***1:**
Only available with firmware version 0A24 and later. In continuous counting mode, the maximum value is ignored. When the count reaches FFFFFFFFh, it restarts from 0 and the overflow flag is set. In this mode, the overflow flag can be cleared by writing zero to the overflow flag register. The default mode is stop counting on overflow.

M-7080B

Address	Description	Data Format	Attribute	Factory Default
40001	Counter/frequency value of channel 0 (low word)	0 to 65535	R	-
40002	Counter/frequency value of channel 0 (high word)	0 to 65535	R	-
40003	Counter/frequency value of channel 1 (low word)	0 to 65535	R	-
40004	Counter/frequency value of channel 1 (high word)	0 to 65535	R	-
40065	Max. value of counter 0 (low word)	0 to 65535	R/W	65535
40066	Max. value of counter 0 (high word)	0 to 65535	R/W	65535
40067	Max. value of counter 1 (low word)	0 to 65535	R/W	65535
40068	Max. value of counter 1 (high word)	0 to 65535	R/W	65535
40097	Preset value of counter 0 (low word)	0 to 65535	R/W	0
40098	Preset value of counter 0 (high word)	0 to 65535	R/W	0
40099	Preset value of counter 1 (low word)	0 to 65535	R/W	0
40100	Preset value of counter 1 (high word)	0 to 65535	R/W	0
40161	Low level width threshold in us	2 to 65535	R/W	2
40162	High level width threshold in us	2 to 65535	R/W	2
40163	Low voltage trigger value in 0.1V	0 to 50	R/W	8
40164	High voltage trigger value in 0.1V	0 to 50	R/W	24
00001	DO 0	0: off 1: on	R/W	-
00002	DO 1	0: off 1: on	R/W	-
00065	Overflow flag of counter 0	0: normal 1: overflow	R	-
00066	Overflow flag of counter 1	0: normal 1: overflow	R	-
00129	Input mode of channel 0, 0:non-isolated, 1:isolated	0:non-isolated 1:isolated	R/W	0
00130	Input mode of channel 1, 0:non-isolated, 1:isolated	0:non-isolated 1:isolated	R/W	0
00131	0: gate is low active, 1: gate is high active, when gate control is enabled	0: low active 1: high active	R/W	0
00132	Gate control, 0: enable, 1:disable	0: disable 1: enable	R/W	0
00135	Start(1)/Stop(0) counter 0	0: stop 1: start	R/W	1
00136	Start(1)/Stop(0) counter 1	0: stop 1: start	R/W	1

00139	Enable(1)/disable(0) digital filter	0: disable 1: enable	R/W	0
00142	Frequency gate time, 0:0.1second, 1: 1.0second	0: 0.1s 1: 1.0s	R/W	0
00143	LED configuration, 0:ch0, 1: ch1	0: ch0 1: ch1	R/W	0

NOTE:

When the type code is 52 and registers 40097 ~ 40100 are set, the current counter values are set to the preset values, too.

M-7084

Address	Description	Data Format	Attribute	Factory Default
30001 ~ 30016	Counter/frequency value of channel 0 to 7, two registers for each channel	0 to 65535	R	-
40065 ~ 40080	Maximum value for up counter 0 to 7, two registers for each channel	0 to 65535	R/W	65535
40097 ~ 40112	Preset value of counter 0 to 7, two registers for each channel	0 to 65535	R/W	0
40161	Frequency measurement timeout in 100ms, 1 ~ 255	1 to 255	R/W	1
40162	Low-pass filter time for channel 0 and 1 in us, 1 ~ 32767	1 to 32767	R/W	1
40163	Low-pass filter time for channel 2 and 3 in us, 1 ~ 32767	1 to 32767	R/W	1
40164	Low-pass filter time for channel 4 to 7 in us, 1 ~ 32767	1 to 32767	R/W	1
40257 ~ 40264	Type code of channel 0 to 7 0x50: Up counter 0x51: Frequency 0x54: Up/down counter 0x55: Pulse/direction counter 0x56: Quadrature counter	Refer to description	R/W	0x50
40481	Firmware version (low word)	0x0000	R	0x0000
40482	Firmware version (high word)	0xab0c for ab.c	R	-
40483	Module name (low word)	0x8400	R	0x8400
40484	Module name (high word)	0x0070	R	0x0070
40485	Module address, valid range: 1 ~ 247	1 to 247	R/W	1
40486	Bits 5:0 Baud rate, valid range: 3 ~ 10 Bits 7:6 00: no parity, 1 stop bit 01: no parity, 2 stop bit 02: even parity, 1 stop bit 03: odd parity, 1 stop bit	Bits 5:0, baud rate 03: 1200 04: 2400 05: 4800 06: 9600 07: 19200 08: 38400 09: 57600 0A: 115200 Bits 7:6, parity 00: N81 01: N82 02: E81 03: O81	R/W	6
40488	Modbus response delay time in ms	0 to 30	R/W	0
40489	Host watchdog timeout value, 0 ~ 255, in 0.1s	0 to 255	R/W	255

40490	Start/stop counting, bit 0 for ch0, bit 1 for ch1,etc, 0 to stop and 1 to start	0 to 255	R/W	255
40492	Host watchdog timeout count, write 0 to clear	0 to 65535	R/W	-
00033 ~ 00040	Input status after XOR mask for channel 0 to 7	0: off 1: on	R	-
00041 ~ 00048	Input status after low-pass filter for channel 0 to 7	0: off 1: on	R	-
00065 ~ 00072	Counter overflow status for channel 0 to 7. Write 1 to clear	0: normal 1; overflow	R/W	-
00257	Protocol, 0: DCON, 1: Modbus RTU	0: DCON 1: Modbus RTU	R/W	1
00261	1: enable, 0: disable host watchdog	0: disable 1: enable	R/W	0
00269	Data format for frequency type, 0: hex, 1: float	0: hex 1: float	R/W	0
00270	Host watch dog timeout status, write 1 to clear host watch dog timeout status	0: normal 1: host watchdog timeout	R/W	-
00273	Reset status, 1: first read after powered on, 0: not the first read after powered on	0: not reset 1: reset	R	-
00513 ~ 00520	Write 1 to clear counter 0 ~ 7	1: clear	W	-
00769 ~ 00776	Enable battery backup for counter 0 to 7	0: disable 1: enable	R/W	0
00801 ~ 00808	Automatic switching between high/low frequency mode for frequency measurement of channel 0 to 7	0: disable 1: enable	R/W	1
00833 ~ 00840	High/low frequency mode for frequency measurement of channel 0 to 7	0: low 1: high	R/W	-
00865 ~ 00872	Stop counting on counter overflow for channel 0 to 7	0: disable 1: enable	R/W	0
00897 ~ 00904	Enable low pass filter for channel 0 to 7	0: disable 1: enable	R/W	0
00929 ~ 00936	XOR mask for channel 0 to 7	0: disable 1: enable	R/W	0

M-7088

Address	Description	Data Format	Attribute	Factory Default
00001 ~ 00008	PWM status 0: Stopped 1: Started	0: stopped 1: started	R/W	0
00065 ~ 00072	Overflow of DI counter, write 1 to clear	0: normal 1: overflow	R/W	-
00225 ~ 00232	DI counter status 0: Disabled 1: Enabled	0: disable 1: enable	R/W	1
00257	Protocol 0: DCON 1: Modbus RTU	0: DCON 1: Modbus RTU	R/W	1
00260	Modbus Host Watchdog mode 0: The same as I-7000 series modules (old mode) 1: The AO and DO command will clear Host Watchdog timeout status (new mode)	0: old mode 1: new mode	R/W	0
00261	Host Watchdog 0: Disabled 1: Enabled	0: disable 1: enable	R/W	0
00266	Clear all DI counters	1: clear	W	-
00270	Host Watchdog timeout status, write 1 to clear the Host Watchdog timeout status	0: normal 1: host watchdog timeout	R/W	-
00278	Inverse DI	0: normal 1: inverse	R/W	0
00289	Save all PWM configurations into EEPROM, write 1 to save	1: save	W	-
00865 ~ 00872	PWM mode 0: Burst mode 1: Continuous mode	0: burst 1: continuous	R/W	1
00897 ~ 00904	PWM trigger status 0: Disabled 1: Enabled	0: disable 1: enable	R/W	-

00929 ~ 00936	PWM trigger start 0: Trigger stop 1: Trigger start	0: stop 1: start	R/W	-
00961 ~ 00968	PWM synchronized	0: disable 1: enable	R/W	0
10033 ~ 10040	DI status	0: off 1: on	R	-
10273	Reset status 0: Not the first read after power-on 1: First read after power-on	0: not reset 1: reset	R	-
30001 ~ 30016	DI count 30001=low word of channel 0, 30002=high word of channel 0, etc.	0 to 65535	R	-
30769 ~ 30776	PWM burst count Condition: PWM mode = burst, PWM status = stop	0 to 65535	R	-
30481	Firmware version (low word)	0x0000	R	0x0000
30482	Firmware version (high word)	0xab0c for ab.c	R	-
30483	Module name (low word)	0x8800	R	0x8800
30484	Module name (high word)	0x0070	R	0x0070
40065 ~ 40080	Max DI count value 40065=low word of channel 0, 40066=high word of channel 0, etc.	0 to 65535	R/W	65535
40097 ~ 40112	Preset value of DI count 40097=low word of channel 0, 40104=high word of channel 0, etc.	0 to 65535	R/W	0
40485	The module address, valid range: 1 ~ 247	1 to 247	R/W	1
40705 ~ 40712	PWM duty cycle in 0.1%	1 to 999	R/W	500
40737 ~ 40752	PWM frequency 40737=low word of channel 0, 40738=high word of channel 0, etc.	1 to 500000	R/W	10000
40801 ~ 40808	PWM burst steps	1 to 65535	R/W	1

40486	Bits 5:0 Baud Rate, 0x03 ~ 0x0A																							
	<table border="1"> <tr> <td>Code</td> <td>0x03</td> <td>0x04</td> <td>0x05</td> <td>0x06</td> </tr> <tr> <td>Baud</td> <td>1200</td> <td>2400</td> <td>4800</td> <td>9600</td> </tr> <tr> <td>Code</td> <td>0x07</td> <td>0x08</td> <td>0x09</td> <td>0x0A</td> </tr> <tr> <td>Baud</td> <td>19200</td> <td>38400</td> <td>57600</td> <td>115200</td> </tr> </table>	Code	0x03	0x04	0x05	0x06	Baud	1200	2400	4800	9600	Code	0x07	0x08	0x09	0x0A	Baud	19200	38400	57600	115200	Refer to description	R/W	6
	Code	0x03	0x04	0x05	0x06																			
	Baud	1200	2400	4800	9600																			
Code	0x07	0x08	0x09	0x0A																				
Baud	19200	38400	57600	115200																				
Bits 7:6 00: No parity, 1 stop bit 01: No parity, 2 stop bits 02: Even parity, 1 stop bit 03: Odd parity, 1 stop bit																								
40488	Modbus response delay time in ms, valid range: 0 ~ 30	0 to 30	R/W	0																				
40489	Host Watchdog timeout value, 0 ~ 255, in 0.1s	0 to 255	R/W	255																				
40495	LED configuration	0-7: channel 8: rotate mode 9: by host	R/W	-																				
40496	LED data for host mode	0 to 65535	R/W	-																				
40498	Power-down count	0 to 65535	R/W	-																				